SERVICE MANUAL



AX-5010R
STEREO
INTEGRATED AMPLIFIER



AX-5015R
STEREO
INTEGRATED AMPLIFIER

■ CONTENTS

Safety Precaution 2
Specifications 3
Block Dragram 5
Circuit Description 6
P.C.Boards(Top & Bottom Views) 9
Exploded View 21
Mechanical Parts List 25
Wiring Diagram 27
Electrical Parts List 29
Schematic Diagram 31

Sherwood

Safety Precaution

WARNING

Service should not be attempted by anyone unfamiliar with the necessary precautions on this player. The following precautions are necessary during servicing.

1. Many electrical and mechanical parts in this player have special characteristics often pass unnoticed and the protection afforded by them cannot necessarily be obtained by using replacement components rated for higher voltage, wattage, etc. Replacement parts that have these special safety characteristic are identified in this manual and its supplements : electrical components having such features are identified by a ⚠ in the schematic diagram and the parts list.
   Before replacing any of these components, read the parts list in this manual carefully.
   The use of substitute replacement parts that do not have the same safety characterstics as specified in the parts list may create shock, fire or other hazards.
2. Before returning the set to the customer, always perform an AC leakage current check on the exposed metallic parts of the cabinet, such as terminals, screwheads, metal overlays, etc. to be sure the set is safe to operate without danger of electrical shock. Plug the AC line cord directly into a 120V AC outlet(**120V Version only**).(Do not use a line isolation transformer during this check.) Use an AC voltmeter having 5000Ω per volt or more sensitivity in the following manner : Connect a 1500Ω 10watte resistor paralleled by a 0.15μF 150V AC capacitor, between a known good earth ground(water pipe, conduct, etc.)and the exposed metallic parts, one at a time. Measure the AC voltage across the combination of 1500Ω resistor and 0.15μF capacitor. Reverse the AC plug at the AC outlet and repeat AC voltage measurements for each exposed metallic part. Voltage measured must not exceed 0.3 volts RMS. This corresponds to 0.2mA AC. Any value exceeding this limit constitutes a potential shock hazard and must be corrected immediately.



Specifications

USA/Canadian version

Power output / ch.
Minimum continuous average both channels driven with no more than 0.3% THD.
at 8 ohms 1kHz 85W
at 8 ohms 20Hz to 20kHz 80W
Intermodulation Distortion, 60Hz:7kHz=4:1 SMPTE
50W for AI2110R(100W for AI2115R), output into 8 ohms 0.05%
Damping Factor at 1 kHz into 8 ohms 35
Input Sensitivity for 100W output, 8 ohms at 1 kHz
Phono 2.5mV
Aux / Tuner 150mV
Phono Preamp input overload;
at 1 kHz, 0.1% THD. 150mV
Signal to Noise ratio, IHF "A" wtd. / unwtd.;
Phono ..... 70 / 67dB
CD / Tuner ..... 96 / 86dB
Frequency Response
Phono, RIAA 40 - 20,000 Hz ..... ±0.5dB
CD at 1W, - 3dB ..... 10Hz - 50kHz
Loudness Contour
at 100 Hz ..... + 6dB
at 10kHz ..... + 3dB
Tone Control;
Bass at 100Hz ..... ± 10dB
Treble at 10kHz ..... ± 10dB
Channel Separation at Aux
at 100 Hz 55dB
at 1kHz 55dB
at 10kHz 40dB
Power Consumption ..... Typical 80W(min. 18W, max. 130W)
Power requirements;
A:120V 50Hz for USA / Canadian version
B:120 / 220V 60 / 50Hz for multi - voltage version(switchable)
C:230V 50Hz for general Europian version
D:230V 50Hz for Germanian & Italian version
E:240V 50Hz for British & Australian version
F:230V 50Hz for Swiss & Scandinabian version
Dimensions ..... 400(W) X 118(H) X 245(D)mm
15.7(W) X 4.6(H) X 9.6(D)inches
Weight (net) ..... 8.6kg (17 lbs, 9.6oz)

Europian version

Power output / ch.
IEC standard 63Hz to 12.5kHz 8 ohms,THD 0.7% 83W
DIN standard 1kHz 8 ohms, THD 1.0% 85W
Total Harmonic Distortion at - 6dB rated output 1kHz 8 ohms 0.03%
Intermodulation Distortion at - 6dB rated output 8 ohms 0.04%
Damping Factor at 1 kHz into 8 ohms 35
Input Sensitivity for 80W output at 1 kHz 8 ohms
Phono 2.5mV
Aux / Tuner 150mV

Phono Preamp input overload;
at 1 kHz, 0.1% THD. ····· 150mV
Signal to Noise ratio, IEC "A" wtd. / unwtd.;
Phono:5mV input 2.2kohm shorted and vol. adj. to 80W ····· 76 / 70dB
AUX :500mV input 2.2kohm shorted and vol. adj. to 80W ····· 96 / 86dB
Frequency Response
Phono, RIAA 40 - 20,000 Hz ····· ± 0.5dB
Aux at 1W, - 3dB ····· 10Hz - 50kHz
Loudness Contour
at 100 Hz ····· + 6dB
at 10kHz ····· + 3dB
Tone Control;
Bass at 100Hz ····· ± 10dB
Treble at 10kHz ····· ± 10dB
Power Consumption ····· Max. 350W, min 18W
Power requirements;
A:120V 50Hz for USA / Canadian version
B:120 / 220V 60 / 50Hz for multi-voltage version(switchable)
C:230V 50Hz for general Europian version
D:230V 50Hz for Germanian & Italian version
E:240V 50Hz for British & Australian version
F:230V 50Hz for Swiss & Scandinabian version
Dimensions ····· 400(W) × 118(H) × 245(D)mm
15.7(W) × 4.6(H) × 9.6(D)inches
Weight(net) ····· 8.6kg(17 lbs, 9.6oz)

Note :Specifications and design subject to change without notice for improvements. Component and circuitry are subject to modification to insure best operation under differing local conditions. This manual is based on the European standard, and provides information on regional circuit modification through use of alternate schematic or wiring diagram,and information on regional component variations through use of parts list.

Block Diagram



Circuit Description

Function Assigned(MC68HC059P : IC801)

No.	Terminal	Operating	Remark
1	$\overline{\text{RESET}}$		Q351
2	$\overline{\text{IRQ}}$	5V	
3	PA7(Stand–by relay)	0V	Q352
4	PA6(Deck Pause)		Q354
5	PA5(Strobe)		IC803
6	PA4(Data)		IC302/303
7	PA3(Clock)		IC302/303
8	PA2(Strobe)		IC302
9	PA1(Volume LED)		Q211
10	PA0(Mute)		IC201
11	PB5(Vol. Down)		IC201
12	PB6(Vol. Down)		IC201
13	PB7(Philips Generator)		Q355 for CD, Tuner only
14	Vss		
15	PC7(AC Cord off)	0V	
16	PC6		
17	PC5(Key scan 3)		Key Matrix
18	PC4(Key scan 2)		
19	PC3(Key scan 1)		
20	PC2(Key in 3)	5V	
21	PC1(Key in 2)	0V	
22	PC0(Key in 1)		
23	PD5(Timer in)		
24	NC		Ground
25	PD7(Remocon in)		Q353
26	X		OSC
27	EX		4MHz
28	Vdd		

Key Matrix (IC801)



Pin Assignment(IC302)



Block Diagram (IC302)



- LC 7821 : IC103(Switching IC)



PIN NO.	TERMINAL	DESCRIPTION
1	PHONO	
2	TUNER	input output terminals of
3	CD	audio signal of left channel
4	AUX	
5		Control to the inside
6	VIDEO	analog switch at the serial
7		data
8	TAPE OUTPUT	
9		
10	TAPE INPUT	
11	DAT OUTPUT	
12	VEE	Negative power Supply terminal-15V
13	STROBE	Setial Control terminal
14	DATA	Connect terminal of
15	CLOCK	MB88P 515B
16	VSS	
17	S	Ground terminal

PIN NO.	TERMINAL	DESCRIPTION
18	RES	Reset terminal When power is turned ON.the Condition of the analog switch is not determined.but when this teminal is L all analog switches are OFF.
19	VDD	Power Supply terminal(-15V)
20	DAT OUTPUT	
21	TAPE INPUT	Input Output terminals of
22		audio signal of right
23	TAPE OUTPUT	channel
24		Control to the inside analog
25	VIDEO	switch at the serial data
26		
27	AUX	
28	CD	Power Supply terminal(-15V)
29	TUNER	
30	PHONO	

P.C.Boards(Top & Bottom Views)

MAIN P.C. BOARD 4002121000
(TOP VIEW)



(BOTTOM VIEW)



SW P.C. BOARD 4002121020
(TOP VIEW)



(BOTTOM VIEW)



VOL.LED P.C. BOARD 4002121150 (AX5010R only)

(TOP VIEW)



(BOTTOM VIEW)



ST/BT P.C. BOARD 4002121140

(TOP VIEW)



(BOTTOM VIEW)



FRONT P.C. BOARD 4002121100 (AX5010R only)

(TOP VIEW)



VOL.SEL P.C. BOARD 4002121120 (AX5010R B version only)

(TOP VIEW)



(BOTTOM VIEW)



OUTLET P.C. BOARD 44002121130

(TOP VIEW) (AX5010R Aversion only)



(BOTTOM VIEW)



FRONT P.C. BOARD 4002121100

(BOTTOM VIEW) (AX5010R only)



VOL.LED P.C. BOARD 4002121250 (AX5015R only)

(TOP VIEW)



(BOTTOM VIEW)



(TOP VIEW)



REMOCON P.C. BOARD 4005113400

(TOP VIEW)



(BOTTOM VIEW)



ST/BY P.C. BOARD 4002121240 (AX5015R only)

(TOP VIEW)



(BOTTOM VIEW)



(BOTTOM VIEW) (AX5015R only)

VOL SEL P.C. BOARD 4002121220

(TOP VIEW) (AX5015R B version only)



(BOTTOM VIEW)



S.P P.C. BOARD 4002121050

(TOP VIEW)



(BOTTOM VIEW)



VOL.SEL P.C. BOARD 4002121030

(TOP VIEW) (AX5015R Domestic only)



(BOTTOM VIEW)



OUTLET P.C. BOARD 4002121040

(TOP VIEW) (AX5010R Dversion only)



(BOTTOM VIEW)



INPUT P.C. BOARD 4002121010

(TOP VIEW)



(BOTTOM VIEW)



Electrical Parts List

PRODUCT SAFETY NOTICE : Products marked with a ⚠ have special characteristics important to safety. If you replace any of these components, carefully read the product safety notice of this manual. Don't degraded the safety of the product through improper servicing.
Resistors & Capacitors tolerance, D (± 0.5%), J (± 5%), K (± 10%), M (± 20%), Z (+ 80%, − 20%).

Ref. No	Part No.	Description				Remark
Main Board 4002121000						
Capacitors						
C501L/R	3479247971	Electric SA	4.7㎌	50V	M	
C502L/R	3579681130	Ceramic	680pF	50V	J	
C503L/R	3479233031	Electric SA	33㎌	16V	M	
C504L/R	3579471130	Ceramic	470pF	50V	J	
C505L/R	3579200130	Ceramic	20pF	50V	J	
C506L/R	3579080030	Ceramic	8pF	50V	J	
C507L/R	3579473530	Ceramic	0.047㎌	100V	J	
C508L/R	3479210971	Electric SA	1㎌	50V	M	
C509L/R	3579050030	Ceramic	5pF	50V	J	
C510L/R	3479222071	Electric SA	22㎌	50V	M	
C511L/R	3579101130	Ceramic	100pF	50V	J	
C512L/R	3579101130	Ceramic	100pF	50V	J	
C513L/R	3679473120	Mylar	0.047㎌	100V	J	
C514 - C529L/R	·	Not used !				
C530L/R	3479247971	Electric SA	4.7㎌	50V	M	
C531L/R	3679473120	Mylar	0.047㎌	100V	J	
C532	3479210061	Electric SA	10㎌	35V	M	
C533	3409247169	Electric SA	47㎌	35V	M	
C534	3479247971	Electric SA	4.7㎌	50V	M	
C535	3479222041	Electric SA	22㎌	25V	M	
C536	3409247111	Electric SA	470㎌	6.3V	M	
C537	3479247041	Electric SA	47㎌	25V	M	
	·					
C550 - C554	3509103450	Ceramic	0.01㎌	500V	J	
C555/C556	3579103530	Ceramic	0.01㎌	50V	J	D
C557/C558	3409247169	Electric SA	470㎌	35V	M	
C559	3479210061	Electric SA	10㎌	35V	M	
C560	3409222141	Electric SA	220㎌	25V	M	
C561	3479247031	Electric SA	47㎌	16V	M	
C562	3409247139	Electric SA	470㎌	16V	M	
C563	3479210971	Electric SA	1㎌	50V	M	
C464	·	Not used !				
C565/C566	3479568280	Electric SA	6800㎌	63V	M	
Connectors						
CNT503 - P	4119104223	Ass'y 4P 220mm to Front B'D				
CNT505	4119103302	Ass'y 3P 330mm to Main B'D				
CNT506 - P	4119104303	Ass'y 4P 300mm to SP B'D				
CNT513 - P	4119106303	Ass'y 6P 300mm to Front B'D				
CNT515 - P	4119102163	Ass'y 2P 160mm to Posistor B'D				
CNT507 - P	4119106263	Ass'y 6P 260mm to S/W B'D				
Diodes						
D501	2258599116	Zener, DZ 12BM				
D502L/R	2058306101	1N4148				
D503L/R	2258599116	Zener, DZ 12BM				Domestic
D504 - D529	·	Not used !				
D530L/R	2058306101	1N4148				
D531L/R	2058306101	1N4148				
D532	2058306101	1N4148				
D533	2258599116	Zener, DZ 12BM				
D536	2258599109	Zener, DZ 15BM				
D534/D535	2058306101	1N4148				
D537 - D539	2258106100	1N4002				

Ref. No	Part No.	Description	Remark
D540 - D549	·	Not used !	
D550 - D553	2058100105	1N5402	
D554	2258599109	15BM	
D555 - D563	2258106100	1N4002	
Fuses			
F501 - F502	5508301635	T 500mA/250V	C,D,E,F
F501 - F502	5508201630	NB 500mA/250V	Domestic, B
	5508201621	NB 500mA/125V	A
F503	5508301135	T 200mA/250V	C,D,E,F
	5508101130	SB 200mA/250V	Domestic, B
	5508101121	SB 200mA/125V	A
IC's			
IC501	2168601105	GD7815	
IC502	2168601101	GD7805	
Resistors:All Resistors are 1/5W carbon film ±5% tolerance, unless otherwise specified. M is metal film, M.O is metal oxide and C is cement type.			
R501L/R	3069332970	3.3kΩ	
R502	3069105970	1MΩ	
R503	3069103970	10kΩ	
R504	3069332970	3.3kΩ	
R505L/R	3069102970	1kΩ	
R506L/R	3069471970	470Ω	
R507L/R	3069563970	56kΩ	
R508L/R	3069681970	680Ω	
R509L/R	3069103970	10kΩ	
R510L/R	3069221970	220Ω	
R511L/R	3069472970	4.7kΩ	
R512L/R	3069621970	620Ω	
R513L/R	3069103970	10kΩ	
R514L/R	3069203970	2kΩ	
R515L/R	3069221970	220Ω	
R516L/R	3069221970	220Ω	
R517L/R	3069680970	68Ω	
R518L/R	3069563970	56kΩ	
R519L/R	3069472970	4.7kΩ	
R520L/R	3069103970	10kΩ	
R521L/R	3069471970	470Ω	
R522L/R	3069392970	3.9kΩ	
R523L/R	3069182970	1.8kΩ	
R524L/R	3069103970	10kΩ	
R525L/R	3059478782	C, 0.47Ω 5W	
R526L/R	3059478782	C, 0.47Ω 5W	
R527 - R529	·	Not used !	
R530L/R	3069472970	4.7kΩ	
R531L/R	3069222970	2.2kΩ	
R532L/R	3069153970	15kΩ	
R533L/R	3039100476	M.O 10Ω 1W	
R534L/R	3039100476	M.O 10Ω 1W	
R535L/R	3069473970	47kΩ	
R536L/R	3069101970	100Ω	
R537L/R	3069103970	10kΩ	
R538L/R	3069473970	47kΩ	
R539L/R	3069223970	22kΩ	

Ref. No	Part No.	Description	Remark
R540	3039222476	2.2kΩ M.O 1W	
R541	3069473970	47kΩ	
R542	3069105970	1MΩ	
R543	3069243970	24kΩ	
R544	3069223970	22kΩ	
R545	3069152970	1.5kΩ	
R546	3069101970	100Ω	
R547	3039479476	4.7Ω M.O 1W	
R548	3069562970	5.6kΩ	
R549L/R	3069123970	12kΩ	
R550	3039100476	M.O, 10Ω 1W	
R551	3039271476	270Ω 1W	
R552	3069331970	330Ω	
R553	3039220476	M.O, 22Ω 1W	
R554	3039339476	3.3Ω1W	
Relay			
Relay1	5528001510	DE 24V/3A	
Relay2	5528001510	VS 12MB - NR 12V	
Transistors			
Q501L/R	2208606112	KTC 1302S	
Q502	2208206105	KTA 1015Y	
Q503L/R	2208606108	KTC 2240B	
Q504L/R	2208606108	KTC 2240BL	
Q505L/R	2208206105	KTA 1015Y	
Q506L/R	2028206102	KTA 949Y	
Q507	2208606104	KTC 1815Y	
Q508	2208606114	MPS A06	
Q509	2008607113	2SC 3421Y	
Q510	2008207106	2SA 1358Y	
Q511	2028116104	2SA 1490	
Q512	2028416107	2SC 3854	
Q513 - Q529	·	Not used !	
Q530	2208606114	MPS A06	
Q531	2208606104	KTC 1815Y	
Q532	2208206105	KTA 1015Y	
Q533	2208606104	KTC 1815Y	
Q534 - Q536	2208606104	MPS A06	
Q537 - Q549	·	Not used !	
Q550	2208606104	MPS A06	

Front Board 4002121100

Capacitors

C301L/R	3679223120	Mylar	0.022μF	100V	J	
C302L/R	3679223120	Mylar	0.022μF	100V	J	
C303L/R	3579561130	Ceramic	560pF	50V	J	
C304L/R	3579470130	Ceramic	47pF	50V	J	
C305L/R	3479247971	Electric SA	4.7μF	50V	M	
C306L/R	3579561130	Ceramic	560pF	50V	J	
C307/C308	3479247031	Electric SA	47μF	16V	M	
C309 - C320	·	Not used !				
C321L/R	3579151130	Ceramic	150pF	50V	J	AX5010R only
C321L/R	3579471130	Ceramic	470pF	50V	J	AX5015R only
C322L/R	3679473120	Mylar	0.0047μF	100V	J	AX5010R only
C322L/R	3679683120	Mylar	0.068μF	100V	J	AX5015R only
C323 - C350	·	Not used !				
C351	3579102130	Ceramic	0.001μF	50V	J	AX5010R only
C351	3439147312	Ceramic	0.047μF	5.3V	J	AX5015R only
C352	3439147312	Electric SA	0.047μF	5.3V	M	AX5010R only
C352	3579102130	Ceramic	0.001μF	50V	J	AX5015R only
C353	3479210971	Electric SA	1μF	50V	M	
C354	3479210061	Electric SA	10μF	35V	M	
C355/C356	3529220210	Ceramic	22pF	50V	J	
C357	3579101130	Ceramic	100pF	50V	J	AX5010R only
C357	3579210871	Electric	0.1μF	50V	J	AX5015R only
C358	3579471130	Ceramic	470pF	50V	J	

Connectors

CNT301	4119106403	Ass'y 6P 400mm to Input B'D
CNT302	4119109102	Ass'y 9P 100mm to Volume B'D
CNT304	4119102162	Ass'y 2P 160mm to ST/BY B'D
CNT305	4119104223	Ass'y 4P 220mm to Main B'D
CNT312	4119106202	Ass'y 6P 200mm to Volume B'D
CNT315	4119106303	Ass'y 6P 300mm to Main B'D
CNT317	4119102302	Ass'y 2P 220mm to Switch B'D
CNT322	4119104183	Ass'y 4P 180mm to Volume B'D
CNT200	4358103266	Ass'y 3P 260mm to Volume B'D

Diodes

D351	2058306101	1N4148	
D352	2058306101	1N4148	AX5015R only
D560 - D569	2381215501	LED SLR 54YC3	
D570 - D571	2381215701	LED SLR 54URC3	
D572 - D573	2381215501	LED SLR 54YC3	

IC's

IC301	2168206104	KIA 75559P	
IC302	2138309139	MC 68HC05P1	
IC303	2138009115	MC 14094	AX5010R only
IC303	2168801100	GL 393	AX5015R only

Resistors

R301L/R	3069223970	22kΩ	
R302L/R	3069333970	33kΩ	
R303	·	Not used !	
R304L/R	3069223970	22kΩ	
R305L/R	3069203970	20kΩ	
R306L/R	3069225970	2.2MΩ	
R307L/R	3069471970	470Ω	
R308L/R	3069104970	100kΩ	
R309 - R310	3069470970	47Ω	
R311 - R320	·	Not used !	
R321L/R	3069473970	47kΩ	
R322L/R	3069562970	5.6kΩ	
R322L/R	3069103970	10kΩ	
R323 - R350	·	Not used !	
R351	3069104970	100kΩ	AX5010R only
R351	3069103970	10kΩ	AX5015R only
R352	3069104970	100kΩ	AX5010R only
R352	3069102970	1kΩ	AX5015R only
R353	3069102970	1kΩ	AX5010R only
R353	3069104970	100kΩ	AX5015R only
R354	3069103970	10kΩ	AX5010R only
R354	3069104970	100kΩ	AX5015R only
R355	3069334970	330kΩ	AX5010R only
R355	3069202970	2kΩ	AX5015R only
R356	3069223970	22kΩ	
R357	3069103970	10kΩ	AX5010R only
R357	3069562970	5.6kΩ	AX5015R only
R358/R359	3069472970	4.7kΩ	AX5010R only
R358	3069102970	1kΩ	AX5015R only
R359	3069224970	220kΩ	AX5015R only

Ref. No	Part No.	Description	Remark
R360	3069562970	5.6kΩ	AX5010R only
R360	3069223970	22kΩ	AX5015R only
R361	3069223970	22kΩ	AX5010R only
R361	3069103970	10kΩ	AX5015R only
R362	3069103970	10kΩ	AX5010R only
R363	3069472970	4.7kΩ	AX5010R only
R364	3069223970	22kΩ	AX5010R only
R365	3069103970	10kΩ	AX5010R only
R366	3069102970	1kΩ	AX5010R only
R367 - R369	3069154970	150kΩ	AX5010R only
R370 - R372	3069104970	100kΩ	AX5010R only
R373 – R375	3069474970	470kΩ	AX5010R only
R376 - R378	3069105970	1MΩ	AX5010R only
R379	3069104970	100kΩ	AX5010R only
R380	3069106970	10MΩ	AX5010R only
R381 - R383	3069103970	10kΩ	AX5010R only
R384 - R386	3069104970	100kΩ	AX5010R only
R385	3069103970	10kΩ	AX5010R only
R387 - R392	3069103970	10kΩ	AX5010R only
R393 - 395	3069681970	680kΩ	
R362 - R366	3069154970	150kΩ	AX5015R only
R367 - R371	3069753970	75kΩ	AX5015R only
R372 - R374	3069334970	330kΩ	AX5015R only
R375	3069223970	22kΩ	AX5015R only
R376 - R380	3069103970	10kΩ	AX5015R only
R381	3069102970	1kΩ	AX5015R only
R382	3069335970	3.3MΩ	AX5015R only
R383	3069103970	100kΩ	AX5015R only
R384 - R389	3069103970	10kΩ	AX5015R only
R390 - R392	3069471970	680Ω	AX5015R only
	3938101830	Resonator, CSA 4.00MG	
Transistors			
Q351 - Q361	2208060610 4	KTC 1815Y	AX5010R only
Q351 - Q359	2208060610 4	KTC 1815Y	AX5015R only

Ref.No	Part No.	Description	Remark

Switch Board 4002121020

Capacitors			
C701L/R	3579561130	Ceramic 560pF 50V J	
Connectors			
CNT706 - P	4358112354	Ass'y 12p 350 To Speaker Board	
CNT705	4119106263	Ass'y 6p 260 To Main Board	
Resistors			
R701L/R	3039471576	M.O. 470Ω 2W	

Ref.No	Part No.	Description	Remark

Input Board 4002121010

Capacitors			
C101	3579473530	Ceramic 0.047 μF 50V Z	
C102L/R	3579220130	Ceramic 22pF 50V J	
C103L/R	3579680130	Ceramic 68pF 50V J	
C104L/R	3479210061	Electric SA 10 μF 35V M	
C105L/R	3579100030	Ceramic 10pFF 50V J	
C106L/R	3409210121	Electric SA 100 μF 10V M	
C107L/R	3679182120	Mylar 0.0056 μF 100V J	

Ref. No	Part No.	Description	Remark
C108L/R	3679182120	Mylar 0.0018 μF 100V J	
C109L/R	3579222530	Ceramic 2200pF 50V Z	
C110L/R	3479268871	Electric SA 0.68 μF 50V M	
C111L/R	3679562120	Mylar 0.0056 μF 100V J	
C112/C113	3479247031	Electric SA 47 μF 16V M	
C114 - C119L/R	3579101130	Ceramic 100pF 50V J	D
C120 - C124L/R	3579101130	Ceramic 100pF 50V J	D
C125	3479210971	Electric SA 1 μF 50V M	
C126 - C129	3479247031	Electric SA 47 μF 16V M	
C130L/R	3579471130	Cermic 470pF 50V J	
C131L/R	3479247971	Electric SA 4.7 μF 50V M	
C132L/R	3579471130	Ceramic 470pF 50V J	
C133 - C135L/R	3579101130	Ceramic 100pF 50V J	
Connectors			
CNT102	4119106302	Ass'y 6p 300 to Volume Boards	
CNT103	4119106403	Ass'y 6p 400 to Front Boards	
Coil			
L101L/R	2648601470	Inductor 50μH	D
Diode			
D101	2058306101	1N4148	
IC's			
IC101/IC102	2168206104	KIA 7555OP	
IC103	2168017132	LC 7821	
Resistors			
R101L/R	3069102970	1kΩ	
R102L/R	3069913970	91kΩ	
R103L/R	3069913970	91kΩ	
R104L/R	3069911970	910Ω	
R105L/R	3069564970	560kΩ	
R106L/R	3069433970	43kΩ	
R107L/R	3069471970	470kΩ	
R108L/R	3069104970	100kΩ	
R109 - R110	3069471970	470kΩ	
R111 - R116L/R	3069104970	1kΩ	
R117L/R	3069104970	100kΩ	
R118/R119	306911970	100kΩ	
R120/R121	3069471970	470kΩ	
R123L/R	3069471970	470kΩ	
R124L/R	3069472970	47kΩ	
R125L/R	3069471970	470kΩ	
R126L/R	3069472970	4.7kΩ	
R127L/R	3069102970	1kΩ	
R128L/R	3069102970	1kΩ	
R129/R131	3069103970	10kΩ	

Ref. No	Part No.	Description	Remark

Speaker Board 4002121050

Capacitors			
C601L/R	3579472530	Ceramic 4700pF 50V J	D
C602L/R	3579472530	Ceramic 4700pF 50V J	D
C603 - C610		Not used !	
C611L/R	3579472530	Ceramic 4700pF 50V J	D
C612L/R	3579472530	Ceramic 4700pF 50V J	D
Connectors			
CNT605	4119104303	A'ssy 4p 300 To Main B'D	

Ref. No	Part No.	Description	Remark
CNT607 - P	4358112354	A'ssy 12p 350 To Switch B'D	

Ref.No	Part No.	Description	Remark
Volume Board 4002121110			
Capacitors			
C201L/R	3479247971	Electric SA 4.7㎌ 50V M	
C202L/R	3579470130	Ceramic 47pF 50V J	
C203L/R	3409210121	Electric SA 100㎌ 10V M	
C204L/R	3579331130	Ceramic 330pF 50V J	
C205L/R	3579220130	Ceramic 22pF 50V J	
C206L/R	3479210061	Electric SA 10㎌ 35V M	
C207L/R	3579102530	Ceramic 1000pF 50V J	
C208 - C210	·	Not used !	
C211L - C213	3479210131	Electric SA 100㎌ 16V M	
Connectors			
CNT201	4119106302	Ass'y 6P 300 To input Board	
CNT202	4119102101	Ass'y 2P 100 To Volume LED Board	
CNT203	4119109102	Ass'y 2P 100 To Front Board	
CNT213	4119106202	Ass'y 6P 200 To Front Board	
CNT200	4358103266	Ass'y 3P 260 To Front Board	
IC's			
IC201	2168206104	KIA 75559P	
IC202	2168007204	TA 729 - 1S	
Resistors			
R201L/R	3069102970	1kΩ	
R202L/R	3069473970	47kΩ	
R203L/R	3069472970	4.7kΩ	
R204L/R	3069333970	33kΩ	
R205L/R	3069471970	470Ω	
R206L/R	3069104970	100kΩ	
R207 - R208	3069470970	47kΩ	
R209	·	Not used !	
R209	3069362970	3.6kΩ	AX5015R only
R210	3069362970	3.6kΩ	AX5010R only
R210	3069223970	22kΩ	AX5015R only
R211	3069330970	33Ω	AX5010R only
R211	3069330970	33kΩ	AX5015R only
R212	3069223970	22kΩ	AX5010R only
R212	3069103970	10kΩ	AX5015R only
R213	3069103970	10kΩ	AX5010R only
R213	3069432970	4.3kΩ	AX5015R only
R214	3069432970	4.3kΩ	AX5010R only
R214	3069224970	220kΩ	AX5015R only
Transistor			
Q211	2208206113	MPS A56	

Ref. No	Part No.	Description	Remark
Volume LED Board 4002121150			
Connector			
CNT202	4119102101	Ass'y 2p 100 To Volume Board	
Diode			
D201	2308220140	LED SLC - 22 VR5	

Ref.No	Part No.	Description	Remark
Outlet Board (D) 4002121040/(A) 4002121130			
Fuses			
F901	5508302534	T 2.5V/250V	D
F801	5508202521	NB 2.5A/125V	A

Ref.No	Part No.	Description	Remark
Volume Selector Board(DOM)4002121030/(B) 4002121120			
Fuses			
F801	5508203030	NB 5A/250V	DOM,AX5015R only
F802	5508202530	NB 2.5A/250V	DOM,AX5015R only
F801	5508202030	NB 5A/250V	B
F802	5508202530	NB 2.5A/250V	B

Ref.No	Part No.	Description	Remark
ST/BY Board 40021211140			
Connector			
CNT403	4119102162	Ass'y 2P To Fornt Board	
D401	2308220140	Diode, LED SLD SLC - 22 UR5	

Ref.No	Part No.	Description	Remark
Remocon Board 4003113000/(DOM)4003113000			
Capacitors			
C801	3409247021	Electric 47㎌ 10V	AX5010R only
C802	3579103530	Ceramic 0.01㎌ 50V	AX5010R only
C803 - C804	3579101130	Ceramic 100pF 50V	AX5010R only
C801 - C802	3579101130	Ceramic 100pF 50V	DOM,AX5015R only
C803	3409247021	Electric 47㎌ 10V	DOM,AX5015R only
Diodes			
D802	2408001100	LED IREL2	AX5010R only
D801	2408001100	LED IREL2	DOM,AX5015R only
IC			
IC801	2138313140	MN158141KA - A	AX5010R only
Transistors			
Q801	2208606112	KTD1302S	DOM, AX5015R only
Q802	2208606112	KTD1302S	AX5010R only
Resistors			
R801	3069229970	2.2Ω	AX5010R only
R801 - R805	3069224970	220kΩ	DOM, AX5015R only
	3938001001	Resonator, CSB455E	

Mechanical Parts List

No.	Description	Part No.	Q'ty	Remark
1	Panel Front Black	048501019312	1	Domestic
(1)	Panel Front Black	048501019311	1	AX5010R only
2	Badge	048535032511	1	Domestic
(2)	Badge(Sherwood)	048535031911	1	
3	Knob Tone Black	048545081911	3	
4	Window Display	048555033611	1	
5	Inlay	048535032611	1	
6	Diffuser	8535032810	1	
7	Knob VR	8543032910	1	
8	LED SLC22 VR5	2308220140	2	
9	Shield Motor VR	6165136610	1	
10	VR RK16Y	3208054310	1	AX5010R only
(10)	VR Motor	3208060310	1	Domestic
11	Button Tact (8Key)	8543032810	1	
12	Holder LED	6063004010	1	
13	Button Mono	8545081710	3	
14	Shield Push Switch	6165136810	1	
15	Switch Tact	4658003710	7	
16	Button Direct	8545081810	1	
17	Switch Push Direct	4628056910	1	
18	Sensor	2408000131	1	
19	Washer Plan	8305003810	1	
20	Chassis Front	6122212610	1	
21	Switch Vertical	4658004010	1	
22	Button Tact Power	8545081510	1	
23	Button Speaker	8545081610	2	
24	Switch Push	4628043810	2	
25	Jack Phones	4438006010	1	
26	Bracket Phones	6505107310	1	
27	Shield Tone VR	6165136710	1	
28	Switch Push (3Key)	4628058110	1	
29	LED SLR54YCD	2381215501	12	
30	Power Transformer	2828081907	1	Domestic
(30)	Power Transformer	2828080107	1	D
31	Foot (Gold/R)	046033101711	4	Domestic
(31)	Foot (Gold)	046033101611	4	
32	Switch Push SDJL 4	4618006510	1	Domestic
33	Switch Push SDJL 2	4618006610	1	Domestic
34	Terminal Speaker	4408105510	1	
35	Jack RCA (4P)	4438103410	1	
36	Jack RCA (2PGreen)	4438107610	1	
37	Jack RCA (2PGround)	4438107810	1	
38	Jack RCA (6P)	4438103510	2	
39	Cover Bottom	6122416310	1	
40	Cover Top Black	046122020011	1	
41	Frame Left	6122631210	1	
42	Bracket Heatsink	6503018310	1	
43	Heatsink	7502003010	1	
44	Bracket Heatsink(R)	6505081610	2	
45	Holder Power TR	6515002312	2	
46	Frame Right	6122620310	1	
47	Outlet Black	4448103910	2	Domestic
(47)	Outlet Black	4448102810	2	AB
(47)	Outlet Black	4448103610	2	C,D,F
48	Chassis Back Black	046102029611	1	Domestic
(48)	Chassis Back Black	046102029621	1	A
(48)	Chassis Back Black	046102029631	1	B
(48)	Chassis Back Black	046102029641	1	C
(48)	Chassis Back Black	046102029651	1	D
(48)	Chassis Back Black	046102029661	1	E
(48)	Chassis Back Black	046102029671	1	F
49	Cord Stopper Black	6513000310	1	Domestic
(49)	Cord Stopper Black	6518000710	1	A,B
(49)	Cord Stopper Black	6518000111	1	C,D,E,F
50	Cord AC Power Black	4308001610	1	Domestic
(50)	Cord AC Power Black	4308001410	1	A,B
(50)	Cord AC Power Black	4308000430	1	C,D,F
(50)	Cord AC Power Black	4308003610	1	E
51	Adadter	4428300310	1	Domestic B
52	Plug Jumper	4328204210	2	
53	System Ground	4408104910	1	
54	VR KK12K1240	3208054110	2	
55	VR 100KMN	3208054210	1	
56	LED SLR 54URC	2381215701	2	

Screws

S1	WSAM 4×8 ZNB	8159440083	8	
S2	2 BTC 3×8 ZNB	8109230083	51	
S3	2 BTC 3×6 ZNB	8109230063	20	
S4	2 WPTC 3×8 ZNB	8159230083	4	
S5	2 PTC 4×6 ZNY	8119240061	1	
S6	HEX MSPW 3×12 ZNY	8099130121	4	

Wiring Diagram









Exploded View



Schematic Diagram

AX-5010R(I)



Q 512 L/R	2 SC 3854	
Q 511 L/R	2 SA 1490	
C 565, C 566	6800 / 63	
F501, F502	A	NB 500mA/125V
	B	NB 500mA/250 V
	C.D.F	T 500 mA/250V
F 503	A	SB 200 mA/125V
	B	SB 200 mA/250V
	C. D. F	T 200 mA/250V
F 801	A	NB 2.5A / 125 V
	B	NB 2.5 A / 250 V
F 802	B	NB 5 A / 250 V
F 902	C.D.F	T 2.5A/ 250 V

NOTES 1. Resistance values are indicated in ohms unless otherwise specified (K = 1,000 M = 1,000,000)
2. Capacitance values are shown in microfarads unless otherwise noted (P = micro micro farads.)

CAUTION: Safety precautions to be followed during servicing
1) Since those parts marked with ⚠ are critical parts for safety use the one described parts list.
2) Before returning the receiver to the customer make appropriate leakage current or resistance measurements to determine that exposed parts are properly insulated from the supply circuit.

Schematic Diagram

AX-5010R(II)



Schematic Diagram

AX-5015R(I)


MAIN B'D
4002121000
SW B'D
4002121020
SPKR B'D 4002121050
SPKR A
SPKR B
CNT 705
PLUG 507
PLUG 515
CNT 515
POSISTOR
CNT 551
CNT 552
CNT 516
CNT 502
CNT 503
CNT 805
PLUG 503
F 801
N.B5A/250V
110V
220 V
OUTLET
AC INPUT
110 V/220 V
60 Hz
60V(48 V)
-60V
(-48 V)
24.5V
24.5 V
-43.8V(39.1V) FTZ
-59 V(-48.2V)
~18.2V(17 V)
-18.2V(-17V)
~10.4V(9.9V)
-10.4V(-9.9V)
RELAY 501 -10.4V(-9.9V)
IC 501
7815
IC 502
7805
IN 5402 X 4
IN 4002 X 4
N.B 500mA/250V
N.B200 mA
250V
F 501
F502
F503
F504
F505
F506
F507
F508
F509
F510
F511
F512
F513
F514
F515
F516
F517
F518
F519
F520
F521
F522
F523
F524
F525
F526
F527
F528
F529
F530
F531
F532
F533
F534
F535
F536
F537
F538
F539
F540
F541
F542
F543
F544
F545
F546
F547
F548
F549
F550
F551
F552
F553
F554
F555
F556
F557
F558
F559
F560
F561
F562
F563
F564
F565
F566
F567
F568
F569
F570
F571
F572
F573
F574
F575
F576
F577
F578
F579
F580
F581
F582
F583
F584
F585
F586
F587
F588
F589
F590
F591
F592
F593
F594
F595
F596
F597
F598
F599
F600
F601
F602
F603
F604
F605
F606
F607
F608
F609
F610
F611
F612
F613
F614
F615
F616
F617
F618
F619
F620
F621
F622
F623
F624
F625
F626
F627
F628
F629
F630
F631
F632
F633
F634
F635
F636
F637
F638
F639
F640
F641
F642
F643
F644
F645
F646
F647
F648
F649
F650
F651
F652
F653
F654
F655
F656
F657
F658
F659
F660
F661
F662
F663
F664
F665
F666
F667
F668
F669
F670
F671
F672
F673
F674
F675
F676
F677
F678
F679
F680
F681
F682
F683
F684
F685
F686
F687
F688
F689
F690
F691
F692
F693
F694
F695
F696
F697
F698
F699
F700
F701
F702
F703
F704
F705
F706
F707
F708
F709
F710
F711
F712
F713
F714
F715
F716
F717
F718
F719
F720
F721
F722
F723
F724
F725
F726
F727
F728
F729
F730
F731
F732
F733
F734
F735
F736
F737
F738
F739
F740
F741
F742
F743
F744
F745
F746
F747
F748
F749
F750
F751
F752
F753
F754
F755
F756
F757
F758
F759
F760
F761
F762
F763
F764
F765
F766
F767
F768
F769
F770
F771
F772
F773
F774
F775
F776
F777
F778
F779
F780
F781
F782
F783
F784
F785
F786
F787
F788
F789
F790
F791
F792
F793
F794
F795
F796
F797
F798
F799
F800
F801
F802
F803
F804
F805
F806
F807
F808
F809
F810
F811
F812
F813
F814
F815
F816
F817
F818
F819
F820
F821
F822
F823
F824
F825
F826
F827
F828
F829
F830
F831
F832
F833
F834
F835
F836
F837
F838
F839
F840
F841
F842
F843
F844
F845
F846
F847
F848
F849
F850
F851
F852
F853
F854
F855
F856
F857
F858
F859
F860
F861
F862
F863
F864
F865
F866
F867
F868
F869
F870
F871
F872
F873
F874
F875
F876
F877
F878
F879
F880
F881
F882
F883
F884
F885
F886
F887
F888
F889
F890
F891
F892
F893
F894
F895
F896
F897
F898
F899
F900
F901
F902
F903
F904
F905
F906
F907
F908
F909
F910
F911
F912
F913
F914
F915
F916
F917
F918
F919
F920
F921
F922
F923
F924
F925
F926
F927
F928
F929
F930
F931
F932
F933
F934
F935
F936
F937
F938
F939
F940
F941
F942
F943
F944
F945
F946
F947
F948
F949
F950
F951
F952
F953
F954
F955
F956
F957
F958
F959
F960
F961
F962
F963
F964
F965
F966
F967
F968
F969
F970
F971
F972
F973
F974
F975
F976
F977
F978
F979
F980
F981
F982
F983
F984
F985
F986
F987
F988
F989
F990
F991
F992
F993
F994
F995
F996
F997
F998
F999
F1000
F1001
F1002
F1003
F1004
F1005
F1006
F1007
F1008
F1009
F1010
F1011
F1012
F1013
F1014
F1015
F1016
F1017
F1018
F1019
F1020
F1021
F1022
F1023
F1024
F1025
F1026
F1027
F1028
F1029
F1030
F1031
F1032
F1033
F1034
F1035
F1036
F1037
F1038
F1039
F1040
F1041
F1042
F1043
F1044
F1045
F1046
F1047
F1048
F1049
F1050
F1051
F1052
F1053
F1054
F1055
F1056
F1057
F1058
F1059
F1060
F1061
F1062
F1063
F1064
F1065
F1066
F1067
F1068
F1069
F1070
F1071
F1072
F1073
F1074
F1075
F1076
F1077
F1078
F1079
F1080
F1081
F1082
F1083
F1084
F1085
F1086
F1087
F1088
F1089
F1090
F1091
F1092
F1093
F1094
F1095
F1096
F1097
F1098
F1099
F1100
F1101
F1102
F1103
F1104
F1105
F1106
F1107
F1108
F1109
F1110
F1111
F1112
F1113
F1114
F1115
F1116
F1117
F1118
F1119
F1120
F1121
F1122
F1123
F1124
F1125
F1126
F1127
F1128
F1129
F1130
F1131
F1132
F1133
F1134
F1135
F1136
F1137
F1138
F1139
F1140
F1141
F1142
F1143
F1144
F1145
F1146
F1147
F1148
F1149
F1150
F1151
F1152
F1153
F1154
F1155
F1156
F1157
F1158
F1159
F1160
F1161
F1162
F1163
F1164
F1165
F1166
F1167
F1168
F1169
F1170
F1171
F1172
F1173
F1174
F1175
F1176
F1177
F1178
F1179
F1180
F1181
F1182
F1183
F1184
F1185
F1186
F1187
F1188
F1189
F1190
F1191
F1192
F1193
F1194
F1195
F1196
F1197
F1198
F1199
F1200
F1201
F1202
F1203
F1204
F1205
F1206
F1207
F1208
F1209
F1210
F1211
F1212
F1213
F1214
F1215
F1216
F1217
F1218
F1219
F1220
F1221
F1222
F1223
F1224
F1225
F1226
F1227
F1228
F1229
F1230
F1231
F1232
F1233
F1234
F1235
F1236
F1237
F1238
F1239
F1240
F1241
F1242
F1243
F1244
F1245
F1246
F1247
F1248
F1249
F1250
F1251
F1252
F1253
F1254
F1255
F1256
F1257
F1258
F1259
F1260
F1261
F1262
F1263
F1264
F1265
F1266
F1267
F1268
F1269
F1270
F1271
F1272
F1273
F1274
F1275
F1276
F1277
F1278
F1279
F1280
F1281
F1282
F1283
F1284
F1285
F1286
F1287
F1288
F1289
F1290
F1291
F1292
F1293
F1294
F1295
F1296
F1297
F1298
F1299
F1300
F1301
F1302
F1303
F1304
F1305
F1306
F1307
F1308
F1309
F1310
F1311
F1312
F1313
F1314
F1315
F1316
F1317
F1318
F1319
F1320
F1321
F1322
F1323
F1324
F1325
F1326
F1327
F1328
F1329
F1330
F1331
F1332
F1333
F1334
F1335
F1336
F1337
F1338
F1339
F1340
F1341
F1342
F1343
F1344
F1345
F1346
F1347
F1348
F1349
F1350
F1351
F1352
F1353
F1354
F1355
F1356
F1357
F1358
F1359
F1360
F1361
F1362
F1363
F1364
F1365
F1366
F1367
F1368
F1369
F1370
F1371
F1372
F1373
F1374
F1375
F1376
F1377
F1378
F1379
F1380
F1381
F1382
F1383
F1384
F1385
F1386
F1387
F1388
F1389
F1390
F1391
F1392
F1393
F1394
F1395
F1396
F1397
F1398
F1399
F1400
F1401
F1402
F1403
F1404
F1405
F1406
F1407
F1408
F1409
F1410
F1411
F1412
F1413
F1414
F1415
F1416
F1417
F1418
F1419
F1420
F1421
F1422
F1423
F1424
F1425
F1426
F1427
F1428
F1429
F1430
F1431
F1432
F1433
F1434
F1435
F1436
F1437
F1438
F1439
F1440
F1441
F1442
F1443
F1444
F1445
F1446
F1447
F1448
F1449
F1450
F1451
F1452
F1453
F1454
F1455
F1456
F1457
F1458
F1459
F1460
F1461
F1462
F1463
F1464
F1465
F1466
F1467
F1468
F1469
F1470
F1471
F1472
F1473
F1474
F1475
F1476
F1477
F1478
F1479
F1480
F1481
F1482
F1483
F1484
F1485
F1486
F1487
F1488
F1489
F1490
F1491
F1492
F1493
F1494
F1495
F1496
F1497
F1498
F1499
F1500
F1501
F1502
F1503
F1504
F1505
F1506
F1507
F1508
F1509
F1510
F1511
F1512
F1513
F1514
F1515
F1516
F1517
F1518
F1519
F1520
F1521
F1522
F1523
F1524
F1525
F1526
F1527
F1528
F1529
F1530
F1531
F1532
F1533
F1534
F1535
F1536
F1537
F1538
F1539
F1540
F1541
F1542
F1543
F1544
F1545
F1546
F1547
F1548
F1549
F1550
F1551
F1552
F1553
F1554
F1555
F1556
F1557
F1558
F1559
F1560
F1561
F1562
F1563
F1564
F1565
F1566
F1567
F1568
F1569
F1570
F1571
F1572
F1573
F1574
F1575
F1576
F1577
F1578
F1579
F1580
F1581
F1582
F1583
F1584
F1585
F1586
F1587
F1588
F1589
F1590
F1591
F1592
F1593
F1594
F1595
F1596
F1597
F1598
F1599
F1600
F1601
F1602
F1603
F1604
F1605
F1606
F1607
F1608
F1609
F1610
F1611
F1612
F1613
F1614
F1615
F1616
F1617
F1618
F1619
F1620
F1621
F1622
F1623
F1624
F1625
F1626
F1627
F1628
F1629
F1630
F1631
F1632
F1633
F1634
F1635
F1636
F1637
F1638
F1639
F1640
F1641
F1642
F1643
F1644
F1645
F1646
F1647
F1648
F1649
F1650
F1651
F1652
F1653
F1654
F1655
F1656
F1657
F1658
F1659
F1660
F1661
F1662
F1663
F1664
F1665
F1666
F1667
F1668
F1669
F1670
F1671
F1672
F1673
F1674
F1675
F1676
F1677
F1678
F1679
F1680
F1681
F1682
F1683
F1684
F1685
F1686
F1687
F1688
F1689
F1690
F1691
F1692
F1693
F1694
F1695
F1696
F1697
F1698
F1699
F1700
F1701
F1702
F1703
F1704
F1705
F1706
F1707
F1708
F1709
F1710
F1711
F1712
F1713
F1714
F1715
F1716
F1717
F1718
F1719
F1720
F1721
F1722
F1723
F1724
F1725
F1726
F1727
F1728
F1729
F1730
F1731
F1732
F1733
F1734
F1735
F1736
F1737
F1738
F1739
F1740
F1741
F1742
F1743
F1744
F1745
F1746
F1747
F1748
F1749
F1750
F1751
F1752
F1753
F1754
F1755
F1756
F1757
F1758
F1759
F1760
F1761
F1762
F1763
F1764
F1765
F1766
F1767
F1768
F1769
F1770
F1771
F1772
F1773
F1774
F1775
F1776
F1777
F1778
F1779
F1780
F1781
F1782
F1783
F1784
F1785
F1786
F1787
F1788
F1789
F1790
F1791
F1792
F1793
F1794
F1795
F1796
F1797
F1798
F1799
F1800
F1801
F1802
F1803
F1804
F1805
F1806
F1807
F1808
F1809
F1810
F1811
F1812
F1813
F1814
F1815
F1816
F1817
F1818
F1819
F1820
F1821
F1822
F1823
F1824
F1825
F1826
F1827
F1828
F1829
F1830
F1831
F1832
F1833
F1834
F1835
F1836
F1837
F1838
F1839
F1840
F1841
F1842
F1843
F1844
F1845
F1846
F1847
F1848
F1849
F1850
F1851
F1852
F1853
F1854
F1855
F1856
F1857
F1858
F1859
F1860
F1861
F1862
F1863
F1864
F1865
F1866
F1867
F1868
F1869
F1870
F1871
F1872
F1873
F1874
F1875
F1876
F1877
F1878
F1879
F1880
F1881
F1882
F1883
F1884
F1885
F1886
F1887
F1888
F1889
F1890
F1891
F1892
F1893
F1894
F1895
F1896
F1897
F1898
F1899
F1900
F1901
F1902
F1903
F1904
F1905
F1906
F1907
F1908
F1909
F1910
F1911
F1912
F1913
F1914
F1915
F1916
F1917
F1918
F1919
F1920
F1921
F1922
F1923
F1924
F1925
F1926
F1927
F1928
F1929
F1930
F1931
F1932
F1933
F1934
F1935
F1936
F1937
F1938
F1939
F1940
F1941
F1942
F1943
F1944
F1945
F1946
F1947
F1948
F1949
F1950
F1951
F1952
F1953
F1954
F1955
F1956
F1957
F1958
F1959
F1960
F1961
F1962
F1963
F1964
F1965
F1966
F1967
F1968
F1969
F1970
F1971
F1972
F1973
F1974
F1975
F1976
F1977
F1978
F1979
F1980
F1981
F1982
F1983
F1984
F1985
F1986
F1987
F1988
F1989
F1990
F1991
F1992
F1993
F1994
F1995
F1996
F1997
F1998
F1999
F2000
F2001
F2002
F2003
F2004
F2005
F2006
F2007
F2008
F2009
F2010
F2011
F2012
F2013
F2014
F2015
F2016
F2017
F2018
F2019
F2020
F2021
F2022
F2023
F2024
F2025
F2026
F2027
F2028
F2029
F2030
F2031
F2032
F2033
F2034
F2035
F2036
F2037
F2038
F2039
F2040
F2041
F2042
F2043
F2044
F2045
F2046
F2047
F2048
F2049
F2050
F2051
F2052
F2053
F2054
F2055
F2056
F2057
F2058
F2059
F2060
F2061
F2062
F2063
F2064
F2065
F2066
F2067
F2068
F2069
F2070
F2071
F2072
F2073
F2074
F2075
F2076
F2077
F2078
F2079
F2080
F2081
F2082
F2083
F2084
F2085
F2086
F2087
F2088
F2089
F2090
F2091
F2092
F2093
F2094
F2095
F2096
F2097
F2098
F2099
F2100
F2101
F2102
F2103
F2104
F2105
F2106
F2107
F2108
F2109
F2110
F2111
F2112
F2113
F2114
F2115
F2116
F2117
F2118
F2119
F2120
F2121
F2122
F2123
F2124
F2125
F2126
F2127
F2128
F2129
F2130
F2131
F2132
F2133
F2134
F2135
F2136
F2137
F2138
F2139
F2140
F2141
F2142
F2143
F2144
F2145
F2146
F2147
F2148
F2149
F2150
F2151
F2152
F2153
F2154
F2155
F2156
F2157
F2158
F2159
F2160
F2161
F2162
F2163
F2164
F2165
F2166
F2167
F2168
F2169
F2170
F2171
F2172
F2173
F2174
F2175
F2176
F2177
F2178
F2179
F2180
F2181
F2182
F2183
F2184
F2185
F2186
F2187
F2188
F2189
F2190
F2191
F2192
F2193
F2194
F2195
F2196
F2197
F2198
F2199
F2200
F2201
F2202
F2203
F2204
F2205
F2206
F2207
F2208
F2209
F2210
F2211
F2212
F2213
F2214
F2215
F2216
F2217
F2218
F2219
F2220
F2221
F2222
F2223
F2224
F2225
F2226
F2227
F2228
F2229
F2230
F2231
F2232
F2233
F2234
F2235
F2236
F2237
F2238
F2239
F2240
F2241
F2242
F2243
F2244
F2245
F2246
F2247
F2248
F2249
F2250
F2251
F2252
F2253
F2254
F2255
F2256
F2257
F2258
F2259
F2260
F2261
F2262
F2263
F2264
F2265
F2266
F2267
F2268
F2269
F2270
F2271
F2272
F2273
F2274
F2275
F2276
F2277
F2278
F2279
F2280
F2281
F2282
F2283
F2284
F2285
F2286
F2287
F2288
F2289
F2290
F2291
F2292
F2293
F2294
F2295
F2296
F2297
F2298
F2299
F2300
F2301
F2302
F2303
F2304
F2305
F2306
F2307
F2308
F2309
F2310
F2311
F2312
F2313
F2314
F2315
F2316
F2317
F2318
F2319
F2320
F2321
F2322
F2323
F2324
F2325
F2326
F2327
F2328
F2329
F2330
F2331
F2332
F2333
F2334
F2335
F2336
F2337
F2338
F2339
F2340
F2341
F2342
F2343
F2344
F2345
F2346
F2347
F2348
F2349
F2350
F2351
F2352
F2353
F2354
F2355
F2356
F2357
F2358
F2359
F2360
F2361
F2362
F2363
F2364
F2365
F2366
F2367
F2368
F2369
F2370
F2371
F2372
F2373
F2374
F2375
F2376
F2377
F2378
F2379
F2380
F2381
F2382
F2383
F2384
F2385
F2386
F2387
F2388
F2389
F2390
F2391
F2392
F2393
F2394
F2395
F2396
F2397
F2398
F2399
F2400
F2401
F2402
F2403
F2404
F2405
F2406
F2407
F2408
F2409
F2410
F2411
F2412
F2413
F2414
F2415
F2416
F2417
F2418
F2419
F2420
F2421
F2422
F2423
F2424
F2425
F2426
F2427
F2428
F2429
F2430
F2431
F2432
F2433
F2434
F2435
F2436
F2437
F2438
F2439
F2440
F2441
F2442
F2443
F2444
F2445
F2446
F2447
F2448
F2449
F2450
F2451
F2452
F2453
F2454
F2455
F2456
F2457
F2458
F2459
F2460
F2461
F2462
F2463
F2464
F2465
F2466
F2467
F2468
F2469
F2470
F2471
F2472
F2473
F2474
F2475
F2476
F2477
F2478
F2479
F2480
F2481
F2482
F2483
F2484
F2485
F2486
F2487
F2488
F2489
F2490
F2491
F2492
F2493
F2494
F2495
F2496
F2497
F2498
F2499
F2500
F2501
F2502
F2503
F2504
F2505
F2506
F2507
F2508
F2509
F2510
F2511
F2512
F2513
F2514
F2515
F2516
F2517
F2518
F2519
F2520
F2521
F2522
F2523
F2524
F2525
F2526
F2527
F2528
F2529
F2530
F2531
F2532
F2533
F2534
F2535
F2536
F2537
F2538
F2539
F2540
F2541
F2542
F2543
F2544
F2545
F2546
F2547
F2548
F2549
F2550
F2551
F2552
F2553
F2554
F2555
F2556
F2557
F2558
F2559
F2560
F2561
F2562
F2563
F2564
F2565
F2566
F2567
F2568
F2569
F2570
F2571
F2572
F2573
F2574
F2575
F2576
F2577
F2578
F2579
F2580
F2581
F2582
F2583
F2584
F2585
F2586
F2587
F2588
F2589
F2590
F2591
F2592
F2593
F2594
F2595
F2596
F2597
F2598
F2599
F2600
F2601
F2602
F2603
F2604
F2605
F2606
F2607
F2608
F2609
F2610
F2611
F2612
F2613
F2614
F2615
F2616
F2617
F2618
F2619
F2620
F2621
F2622
F2623
F2624
F2625
F2626
F2627
F2628
F2629
F2630
F2631
F2632
F2633
F2634
F2635
F2636
F2637
F2638
F2639
F2640
F2641
F2642
F2643
F2644
F2645
F2646
F2647
F2648
F2649
F2650
F2651
F2652
F2653
F2654
F2655
F2656
F2657
F2658
F2659
F2660
F2661
F2662
F2663
F2664
F2665
F2666
F2667
F2668
F2669
F2670
F2671
F2672
F2673
F2674
F2675
F2676
F2677
F2678
F2679
F2680
F2681
F2682
F2683
F2684
F2685
F2686
F2687
F2688
F2689
F2690
F2691
F2692
F2693
F2694
F2695
F2696
F2697
F2698
F2699
F2700
F2701
F2702
F2703
F2704
F2705
F2706
F2707
F2708
F2709
F2710
F2711
F2712
F2713
F2714
F2715
F2716
F2717
F2718
F2719
F2720
F2721
F2722
F2723
F2724
F2725
F2726
F2727
F2728
F2729
F2730
F2731
F2732
F2733
F2734
F2735
F2736
F2737
F2738
F2739
F2740
F2741
F2742
F2743
F2744
F2745
F2746
F2747
F2748
F2749
F2750
F2751
F2752
F2753
F2754
F2755
F2756
F2757
F2758
F2759
F2760
F2761
F2762
F2763
F2764
F2765
F2766
F2767
F2768
F2769
F2770
F2771
F2772
F2773
F2774
F2775
F2776
F2777
F2778
F2779
F2780
F2781
F2782
F2783
F2784
F2785
F2786
F2787
F2788
F2789
F2790
F2791
F2792
F2793
F2794
F2795
F2796
F2797
F2798
F2799
F2800
F2801
F2802
F2803
F2804
F2805
F2806
F2807
F2808
F2809
F2810
F2811
F2812
F2813
F2814
F2815
F2816
F2817
F2818
F2819
F2820
F2821
F2822
F2823
F2824
F2825
F2826
F2827
F2828
F2829
F2830
F2831
F2832
F2833
F2834
F2835
F2836
F2837
F2838
F2839
F2840
F2841
F2842
F2843
F2844
F2845
F2846
F2847
F2848
F2849
F2850
F2851
F2852
F2853
F2854
F2855
F2856
F2857
F2858
F2859
F2860
F2861
F2862
F2863
F2864
F2865
F2866
F2867
F2868
F2869
F2870
F2871
F2872
F2873
F2874
F2875
F2876
F2877
F2878
F2879
F2880
F2881
F2882
F2883
F2884
F2885
F2886
F2887
F2888
F2889
F2890
F2891
F2892
F2893
F2894
F2895
F2896
F2897
F2898
F2899
F2900
F2901
F2902
F2903
F2904
F2905
F2906
F2907
F2908
F2909
F2910
F2911
F2912
F2913
F2914
F2915
F2916
F2917
F2918
F2919
F2920
F2921
F2922
F2923
F2924
F2925
F2926
F2927
F2928
F2929
F2930
F2931
F2932
F2933
F2934
F2935
F2936
F2937
F2938
F2939
F2940
F2941
F2942
F2943
F2944
F2945
F2946
F2947
F2948
F2949
F2950
F2951
F2952
F2953
F2954
F2955
F2956
F2957
F2958
F2959
F2960
F2961
F2962
F2963
F2964
F2965
F2966
F2967
F2968
F2969
F2970
F2971
F2972
F2973
F2974
F2975
F2976
F2977
F2978
F2979
F2980
F2981
F2982
F2983
F2984
F2985
F2986
F2987
F2988
F2989
F2990
F2991
F2992
F2993
F2994
F2995
F2996
F2997
F2998
F2999
F3000
F3001
F3002
F3003
F3004
F3005
F3006
F3007
F3008
F3009
F3010
F3011
F3012
F3013
F3014
F3015
F3016
F3017
F3018
F3019
F3020
F3021
F3022
F3023
F3024
F3025
F3026
F3027
F3028
F3029
F3030
F3031
F3032
F3033
F3034
F3035
F3036
F3037
F3038
F3039
F3040
F3041
F3042
F3043
F3044
F3045
F3046
F3047
F3048
F3049
F3050
F3051
F3052
F3053
F3054
F3055
F3056
F3057
F3058
F3059
F3060
F3061
F3062
F3063
F3064
F3065
F3066
F3067
F3068
F3069
F3070
F3071
F3072
F3073
F3074
F3075
F3076
F3077
F3078
F3079
F3080
F3081
F3082
F3083
F3084
F3085
F3086
F3087
F3088
F3089
F3090
F3091
F3092
F3093
F3094
F3095
F3096
F3097
F3098
F3099
F3100
F3101
F3102
F3103
F3104
F3105
F3106
F3107
F3108
F3109
F3110
F3111
F3112
F3113
F3114
F3115
F3116
F3117
F3118
F3119
F3120
F3121
F3122
F3123
F3124
F3125
F3126
F3127
F3128
F3129
F3130
F3131
F3132
F3133
F3134
F3135
F3136
F3137
F3138
F3139
F3140
F3141
F3142
F3143
F3144
F3145
F3146
F3147
F3148
F3149
F3150
F3151
F3152
F3153
F3154
F3155
F3156
F3157
F3158
F3159
F3160
F3161
F3162
F3163
F3164
F3165
F3166
F3167
F3168
F3169
F3170
F3171
F3172
F3173
F3174
F3175
F3176
F3177
F3178
F3179
F3180
F3181
F3182
F3183
F3184
F3185
F3186
F3187
F3188
F3189
F3190
F3191
F3192
F3193
F3194
F3195
F3196
F3197
F3198
F3199
F3200
F3201
F3202
F3203
F3204
F3205
F3206
F3207
F3208
F3209
F3210
F3211
F3212
F3213
F3214
F3215
F3216
F3217
F3218
F3219
F3220
F3221
F3222
F3223
F3224
F3225
F3226
F3227
F3228
F3229
F3230
F3231
F3232
F3233
F3234
F3235
F3236
F3237
F3238
F3239
F3240
F3241
F3242
F3243
F3244
F3245
F3246
F3247
F3248
F3249
F3250
F3251
F3252
F3253
F3254
F3255
F3256
F3257
F3258
F3259
F3260
F3261
F3262
F3263
F3264
F3265
F3266
F3267
F3268
F3269
F3270
F3271
F3272
F3273
F3274
F3275
F3276
F3277
F3278
F3279
F3280
F3281
F3282
F3283
F3284
F3285
F3286
F3287
F3288
F3289
F3290
F3291
F3292
F3293
F3294
F3295
F3296
F3297
F3298
F3299
F3300
F3301
F3302
F3303
F3304
F3305
F3306
F3307
F3308
F3309
F3310
F3311
F3312
F3313
F3314
F3315
F3316
F3317
F3318
F3319
F3320
F3321
F3322
F3323
F3324
F3325
F3326
F3327
F3328
F3329
F3330
F3331
F3332
F3333
F3334
F3335
F3336
F3337
F3338
F3339
F3340
F3341
F3342
F3343
F3344
F3345
F3346
F3347
F3348
F3349
F3350
F3351
F3352
F3353
F3354
F3355
F3356
F3357
F3358
F3359
F3360
F3361
F3362
F3363
F3364
F3365
F3366
F3367
F3368
F3369
F3370
F3371
F3372
F3373
F3374
F3375
F3376
F3377
F3378
F3379
F3380
F3381
F3382
F3383
F3384
F3385
F3386
F3387
F3388
F3389
F3390
F3391
F3392
F3393
F3394
F3395
F3396
F3397
F3398
F3399
F3400
F3401
F3402
F3403
F3404
F3405
F3406
F3407
F3408
F3409
F3410
F3411
F3412
F3413
F3414
F3415
F3416
F3417
F3418
F3419
F3420
F3421
F3422
F3423
F3424
F3425
F3426
F3427
F3428
F3429
F3430
F3431
F3432
F3433
F3434
F3435
F3436
F3437
F3438
F3439
F3440
F3441
F3442
F3443
F3444
F3445
F3446
F3447
F3448
F3449
F3450
F3451
F3452
F3453
F3454
F3455
F3456
F3457
F3458
F3459
F3460
F3461
F3462
F3463
F3464
F3465
F3466
F3467
F3468
F3469
F3470
F3471
F3472
F3473
F3474
F3475
F3476
F3477
F3478
F3479
F3480
F3481
F3482
F3483
F3484
F3485
F3486
F3487
F3488
F3489
F3490
F3491
F3492
F3493
F3494
F3495
F3496
F3497
F3498
F3499
F3500
F3501
F3502
F3503
F3504
F3505
F3506
F3507
F3508
F3509
F3510
F3511
F3512
F3513
F3514
F3515
F3516
F3517
F3518
F3519
F3520
F3521
F3522
F3523
F3524
F3525
F3526
F3527
F3528
F3529
F3530
F3531
F3532
F3533
F3534
F3535
F3536
F3537
F3538
F3539
F3540
F3541
F3542
F3543
F3544
F3545
F3546
F3547
F3548
F3549
F3550
F3551
F3552
F3553
F3554
F3555
F3556
F3557
F3558
F3559
F3560
F3561
F3562
F3563
F3564
F3565
F3566
F3567
F3568
F3569
F3570
F3571
F3572
F3573
F3574
F3575
F3576
F3577
F3578
F3579
F3580
F3581
F3582
F3583
F3584
F3585
F3586
F3587
F3588
F3589
F3590
F3591
F3592
F3593
F3594
F3595
F3596
F3597
F3598
F3599
F3600
F3601
F3602
F3603
F3604
F3605
F3606
F3607
F3608
F3609
F3610
F3611
F3612
F3613
F3614
F3615
F3616
F3617
F3618
F3619
F3620
F3621
F3622
F3623
F3624
F3625
F3626
F3627
F3628
F3629
F3630
F3631
F3632
F3633
F3634
F3635
F3636
F3637
F3638
F3639
F3640
F3641
F3642
F3643
F3644
F3645
F3646
F3647
F3648
F3649
F3650
F3651
F3652
F3653
F3654
F3655
F3656
F3657
F3658
F3659
F3660
F3661
F3662
F3663
F3664
F3665
F3666
F3667
F3668
F3669
F3670
F3671
F3672
F3673
F3674
F3675
F3676
F3677
F3678
F3679
F3680
F3681
F3682
F3683
F3684
F3685
F3686
F3687
F3688
F3689
F3690
F3691
F3692
F3693
F3694
F3695
F3696
F3697
F3698
F3699
F3700
F3701
F3702
F3703
F3704
F3705
F3706
F3707
F3708
F3709
F3710
F3711
F3712
F3713
F3714
F3715
F3716
F3717
F3718
F3719
F3720
F3721
F3722
F3723
F3724
F3725
F3726
F3727
F3728
F3729
F3730
F3731
F3732
F3733
F3734
F3735
F3736
F3737
F3738
F3739
F3740
F3741
F3742
F3743
F3744
F3745
F3746
F3747
F3748
F3749
F3750
F3751
F3752
F3753
F3754
F3755
F3756
F3757
F3758
F3759
F3760
F3761
F3762
F3763
F3764
F3765
F3766
F3767
F3768
F3769
F3770
F3771
F3772
F3773
F3774
F3775
F3776
F3777
F3778
F3779
F3780
F3781
F3782
F3783
F3784
F3785
F3786
F3787
F3788
F3789
F3790
F3791
F3792
F3793
F3794
F3795
F3796
F3797
F3798
F3799
F3800
F3801
F3802
F3803
F3804
F3805
F3806
F3807
F3808
F3809
F3810
F3811
F3812
F3813
F3814
F3815
F3816
F3817
F3818
F3819
F3820
F3821
F3822
F3823
F3824
F3825
F3826
F3827
F3828
F3829
F3830
F3831
F3832
F3833
F3834
F3835
F3836
F3837
F3838
F3839
F3840
F3841
F3842
F3843
F3844
F3845
F3846
F3847
F3848
F3849
F3850
F3851
F3852
F3853
F3854
F3855
F3856
F3857
F3858
F3859
F3860
F3861
F3862
F3863
F3864
F3865
F3866
F3867
F3868
F3869
F3870
F3871
F3872
F3873
F3874
F3875
F3876
F3877
F3878
F3879
F3880
F3881
F3882
F3883
F3884
F3885
F3886
F3887
F3888
F3889
F3890
F3891
F3892
F3893
F3894
F3895
F3896
F3897
F3898
F3899
F3900
F3901
F3902
F3903
F3904
F3905
F3906
F3907
F3908
F3909
F3910
F3911
F3912
F3913
F3914
F3915
F3916
F3917
F3918
F3919
F3920
F3921
F3922
F3923
F3924
F3925
F3926
F3927
F3928
F3929
F3930
F3931
F3932
F3933
F3934
F3935
F3936
F3937
F3938
F3939
F3940
F3941
F3942
F3943
F3944
F3945
F3946
F3947
F3948
F3949
F3950
F3951
F3952
F3953
F3954
F3955
F3956
F3957
F3958
F3959
F3960
F3961
F3962
F3963
F3964
F3965
F3966
F3967
F3968
F3969
F3970
F3971
F3972
F3973
F3974
F3975
F3976
F3977
F3978
F3979
F3980
F3981
F3982
F3983
F3984
F3985
F3986
F3987
F3988
F3989
F3990
F3991
F3992
F3993
F3994
F3995
F3996
F3997
F3998
F3999
F4000
F4001
F4002
F4003
F4004
F4005
F4006
F4007
F4008
F4009
F4010
F4011
F4012
F4013
F4014
F4015
F4016
F4017
F4018
F4019
F4020
F4021
F4022
F4023
F4024
F4025
F4026
F4027
F4028
F4029
F4030
F4031
F4032
F4033
F4034
F4035
F4036
F4037
F4038
F4039
F4040
F4041
F4042
F4043
F4044
F4045
F4046
F4047
F4048
F4049
F4050
F4051
F4052
F4053
F4054
F4055
F4056
F4057
F4058
F4059
F4060
F4061
F4062
F4063
F4064
F4065
F4066
F4067
F4068
F4069
F4070
F4071
F4072
F4073
F4074
F4075
F4076
F4077
F4078
F4079
F4080
F4081
F4082
F4083
F4084
F4085
F4086
F4087
F4088
F4089
F4090
F4091
F4092
F4093
F4094
F4095
F4096
F4097
F4098
F4099
F4100
F4101
F4102
F4103
F4104
F4105
F4106
F4107
F4108
F4109
F4110
F4111
F4112
F4113
F4114
F4115
F4116
F4117
F4118
F4119
F4120
F4121
F4122
F4123
F4124
F4125
F4126
F4127
F4128
F4129
F4130
F4131
F4132
F4133
F4134
F4135
F4136
F4137
F4138
F4139
F4140
F4141
F4142
F4143
F4144
F4145
F4146
F4147
F4148
F4149
F4150
F4151
F4152
F4153
F4154
F4155
F4156
F4157
F4158
F4159
F4160
F4161
F4162
F4163
F4164
F4165
F4166
F4167
F4168
F4169
F4170
F4171
F4172
F4173
F4174
F4175
F4176
F4177
F4178
F4179
F4180
F4181
F4182
F4183
F4184
F4185
F4186
F4187
F4188
F4189
F4190
F4191
F4192
F4193
F4194
F4195
F4196
F4197
F4198
F4199
F4200
F4201
F4202
F4203
F4204
F4205
F4206
F4207
F4208
F4209
F4210
F4211
F4212
F4213
F4214
F4215
F4216
F4217
F4218
F4219
F4220
F4221
F4222
F4223
F4224
F4225
F4226
F4227
F4228
F4229
F4230
F4231
F4232
F4233
F4234
F4235
F4236
F4237
F4238
F4239
F4240
F4241
F4242
F4243
F4244
F4245
F4246
F4247
F4248
F4249
F4250
F4251
F4252
F4253
F4254
F4255
F4256
F4257
F4258
F4259
F4260
F4261
F4262
F4263
F4264
F4265
F4266
F4267
F4268
F4269
F4270
F4271
F4272
F4273
F4274
F4275
F4276
F4277
F4278
F4279
F4280
F4281
F4282
F4283
F4284
F4285
F4286
F4287
F4288
F4289
F4290
F4291
F4292
F4293
F4294
F4295
F4296
F4297
F4298
F4299
F4300
F4301
F4302
F4303
F4304
F4305
F4306
F4307
F4308
F4309
F4310
F4311
F4312
F4313
F4314
F4315
F4316
F4317
F4318
F4319
F4320
F4321
F4322
F4323
F4324
F4325
F4326
F4327
F4328
F4329
F4330
F4331
F4332
F4333
F4334
F4335
F4336
F4337
F4338
F4339
F4340
F4341
F4342
F4343
F4344
F4345
F4346
F4347
F4348
F4349
F4350
F4351
F4352
F4353
F4354
F4355
F4356
F4357
F4358
F4359
F4360
F4361
F4362
F4363
F4364
F4365
F4366
F4367
F4368
F4369
F4370
F4371
F4372
F4373
F4374
F4375
F4376
F4377
F4378
F4379
F4380
F4381
F4382
F4383
F4384
F4385
F4386
F4387
F4388
F4389
F4390
F4391
F4392
F4393
F4394
F4395
F4396
F4397
F4398
F4399
F4400
F4401
F4402
F4403
F4404
F4405
F4406
F4407
F4408
F4409
F4410
F4411
F4412
F4413
F4414
F4415
F4416
F4417
F4418
F4419
F4420
F4421
F4422
F4423
F4424
F4425
F4426
F4427
F4428
F4429
F4430
F4431
F4432
F4433
F4434
F4435
F4436
F4437
F4438
F4439
F4440
F4441
F4442
F4443
F4444
F4445
F4446
F4447
F4448
F4449
F4450
F4451
F4452
F4453
F4454
F4455
F4456
F4457
F4458
F4459
F4460
F4461
F4462
F4463
F4464
F4465
F4466
F4467
F4468
F4469
F4470
F4471
F4472
F4473
F4474
F4475
F4476
F4477
F4478
F4479
F4480
F4481
F4482
F4483
F4484
F4485
F4486
F4487
F4488
F4489
F4490
F4491
F4492
F4493
F4494
F4495
F4496
F4497
F4498
F4499
F4500
F4501
F4502
F4503
F4504
F4505
F4506
F4507
F4508
F4509
F4510
F4511
F4512
F4513
F4514
F4

Schematic Diagram
AX-5015R(Ⅱ)



WARNING: CHEMICAL CONTENT NOTICE!

The solder used in the production of this product contains LEAD. In addition, other electrical/electronic and/or plastic (where applicable) components may also contain traces of chemicals found by the California Health and Welfare Agency (and possibly other entities) to cause cancer and/or birth defects or other reproductive harm.

DO NOT PLACE SOLDER, ELECTRICAL/ELECTRONIC OR PLASTIC COMPONENTS IN YOUR MOUTH FOR ANY REASON WHATSOEVER!

Avoid prolonged, unprotected contact between solder and your skin! When soldering, do not inhale solder fumes or expose eyes to solder/flux vapor!

If you come in contact with solder or components located inside the enclosure of this product, wash your hands before handling food.

■ SPECIFICATIONS

Output Level/Impedance	1.5V/560Ω
Input Sensitivity/Impedance	1.5V/20kΩ
Frequency Response	20Hz—20kHz
Total Harmonic Distortion (20Hz—20kHz)	
Output Level 1.5V,	
20kHz LOW PASS FILTER	Less than 0.03%
Signal-to-Noise Ratio (IHF-A Network)	More than 90dB
Equalizer Band	9-band
Center Frequency	63, 125, 250, 500, 1k, 2k, 4k, 8k, 16kHz
Boost/Attenuation	±12dB (2dB per a step)
Subwoofer Frequency	
(THROUGH, 130Hz, 80Hz)	–6dB/oct.
Audio Muting	–20dB
DSP Preset Programs	8 (HALL, CHAMBER CHURCH, STADIUM, JAZZ CLUB, ROCK CON, DISCO, THEATER)
DSP User Programmable Areas	8
EQ Preset Programs	4 (POPS, VOCAL, CLASSIC, FLAT)
EQ User Programmable Areas	4
Power Supply	14.4V
Power Consumption	800mA (Less than 1mA for memory back up)
Dimensions (W x H x D)	
Main Unit	215 x 52.5 x 162mm (8-7/16" x 2-1/16" x 6-5/16")
Commander Unit	172 x 25 x 49mm (6-3/4" x 1-1/16" x 1-15/16")
Weight	
Main Unit	1.5kg (3lbs. 5oz.)
Commander Unit	0.2kg (7oz.)
Accessories	Commander unit
	4.5m extention cable
	Power cords
	Frame
	Mounting hardware
	Magic fastener x2
	5 x 6 tapping hex screw with washer x4
	M2 x 5 screw x4
	M5 x 8 flat head screw x4
	M5 x 8 hex screw with washer x4

* *Specifications subject to change without notice.*

● **DIMENSIONS**



Unit : mm (inch)

■ BLOCK DIAGRAM



■ INTERNAL VIEW



❶ IC308, 309 : LC7535 (Electric Controlled Volume)
❷ MAIN CIRCUIT BOARD
❸ IC34, 38 : PCM61P (DAC)
❹ DSP CIRCUIT BOARD
❺ IC312 : HD63B01Y0XXXXP (8 bit μ-COM)
❻ I/O CIRCUIT BOARD
❼ IC11 : YM3422 (Digital Signal Format Converter)
❽ IC10, 13 : TC51832FL-10 (RAM)
❾ IC9, 12 : YM3413 (LDSP)
❿ IC14, 15 : YM3433 (Digital Filter)
⓫ IC5 : AK5339-VP (A/D Converter)
⓬ IC6, 7 : YM6104 (Digital Equalizer)
⓭ IC24 : YM3436 (Digital Format Interface Receiver)

■ DISASSEMBLY PROCEDURES

(Remove parts in the order as numbered.)

1. Removal of Top Cover Ass'y

a. Remove 4 screws (①) in Fig. 1.

2. Removal of Shield Plate (B)

a. Removal 5 screws (②, ③) in Fig. 1.



Fig. 1

3. Removal of Main Circuit Board

a. Remove 7 screws (④) in Fig. 2 and then remove the Sub Panel (R).

b. Remove 4 screws (⑤) in Fig. 2 and then remove the Main Circuit Board.

* Remove 3 connectors (#1, #4, #5) from DSP Circuit Board.



Fig. 2

■ CHIP DEVICE DESCRIPTIONS

CAUTION : AFTER REMOVING CHIP DEVICES, DONOT REUSE THEM.

1. KINDS OF CHIP DEVICES

There are five kinds of chip devices :

a. Thick film chip resistors
b. Multi-layer ceramic chip capacitors
c. Mini-mould (Chip) transistors
d. Mini-mould (Chip) diodes
e. Mini-mould (Chip) ICs

2. IDENTIFICATION OF CHIP DEVICES

The first four kinds of chip devices have similar shape and size, and it is quite difficult to identify them at a glance, but basically, the following identification is available:

a. Resistors and Jumper Resistors

The resistance of each chip resistor is indicated by a color code consisting of three color bands.

Color codes

Color	1st color band	2nd color band	3rd color band
	Nominal resistance (Unit : Ω)		
	1st number in code	2nd number in code	Multiplier
Black	0	0	10^0
Brown	1	1	10^1
Red	2	2	10^2
Orange	3	3	10^3
Yellow	4	4	10^4
Green	5	5	10^5
Blue	6	6	
Purple	7	7	
Gray	8	8	
White	9	9	
Gold			10^{-1}



b. Ceramic Capacitors

A color code is used to indicate the capacitance of capacitors less than 1000pF.

Color codes

Color	1st color band	2nd color band	3rd color band
	Nominal capacitance (Unit : pF)		
	1st number in code	2nd number in code	Multiplier
Black	0	0	10^0
Brown	1	1	10^1
Red	2	2	10^2



Capacitors exceeding 1000pF in capacitance have a 2 character indication of the capacitance value. For example, "A3" stands for 1000pF.

Example :



● Indication Code Definitions

Alphabet ..... The numerical value of the electrostatic capacity.
Number ..... The value of the multiplier.
Special mark ..... Temperature characteristic.

● Electrostatic capacity

<Alphabet>

Alphabet	A	B	C	D	E	F	G	H	J	K	L	M
Numerical value	1.0	1.1	1.2	1.3	1.5	1.6	1.8	2.0	2.2	2.4	2.7	3.0

Alphabet	N	P	Q	R	S	T	U	V	W	X	Y	Z
Numerical value	3.3	3.6	3.9	4.3	4.7	5.1	5.6	6.2	6.8	7.5	8.2	9.1

Alphabet	a	b	d	e	f	m	n	t	y
Numerical value	2.5	3.5	4.0	4.5	5.0	6.6	7.6	8.0	9.0

<Number>

Number	0	1	2	3	4	5	6	7	8	9
Multiplier	10^0	10^1	10^2	10^3	10^4	10^5	10^6	10^7	10^8	10^{-1}

c. Transistors

Transistor can be identified by a character code consisting of any combination of letters and numbers. Given below is a cross-reference table of identification codes : use it to identify each device.

Indication	Part No.	Description	HFE rank
BQ	iC241200	Transistor 2SC2412	Q-rank
BR	iC241200	Transistor 2SC2412	R-rank
BS	iC241200	Transistor 2SC2412	S-rank
CCB	VG730700	Transistor 2SC3326	B-rank
14	VB503600	Digital Transistor DTA114EK	
24	VB504700	Digital Transistor DTC114EK	
A3	VK625100	Diode Array	

d. Diodes and Zener Diodes

Each diode has a yellow or white band (cathode band) on its cathode side as shown below:



The zener diode has three color bands as shown below:



The 1st and 2nd color bands indicate the model as a number assigned to each color as listed in Table 1. Referring to Table 1, read the code number by converting the colors of the bands into the corresponding numbers and then find the model code in Table 2.
The number in the model code indicates the zener voltage. The 3rd color band on the zener diode indicates the subdivision of the zener voltage.

COLOR	1st color band 1st number in code	2nd color band 2nd number in code	3rd color band Zener voltage Subdivision
Black	0	0	—
Brown	1	1	—
Red	2	2	—
Orange	3	3	—
Yellow	4	4	A
Green	5	5	B
Blue	6	6	C
Purple	7	7	—
Gray	8	8	—
White	9	9	D

Table 1

RLZ Series Zener Code No. and Model Code Cross-reference Table.

Zener Code No.	Model Code	Zener Code No.	Model Code	Zener Code No.	Model Code
07	RLZ3.6	16	RLZ8.2	25	RLZ20
08	RLZ3.9	17	RLZ9.1	26	RLZ22
09	RLZ4.3	18	RLZ10	27	RLZ24
10	RLZ4.7	19	RLZ11	28	RLZ27
11	RLZ5.1	20	RLZ12	29	RLZ30
12	RLZ5.6	21	RLZ13	30	RLZ33
13	RLZ6.2	22	RLZ15	31	RLZ36
14	RLZ6.8	23	RLZ16	32	RLZ39
15	RLZ7.5	24	RLZ18		

Table 2

As explained above, you can identify chip devices tentatively, but actual identification should be made by referring to the parts layout drawing in the service manual.

3. SPECIAL NOTICE FOR HANDLING CHIP DEVICES

Chip devices are not heatproof or shockproof. Use caution when handling them.

a. For shock provention

Chip devices are made of ceramic moulding, please do not subject them to direct shock.

- Set the chip device flat onto the printed circuit board.
- Do not apply unnecessary stress to the chip device. When soldering two terminals of the chip device, soldering is done one terminal at s time. Sometimes, when one terminal is soldered, the other unsoldered terminal will lift slightly. In these cases, do not try to push down the lifted terminal using the tip of the soldering iron; you may crack the chip device or break the terminals.

b. For heat prevention

Do not apply high temperature to chip devices for long periods. Soldering should be done quickly.

c. Soldering

- Chip devices can not withstand rapid heating or cooling. Do not heat the chip itself; heat the terminals of chip devices only.
- Solder quickly, excessive soldering time will cause damage to chip devices.
- Try to reduce amount of solder when soldering. The mount of solder will effect the extent of chip bending against the printed circuit board. Refer to the proper amount of solder as shown below.



Fig. 5

d. Soldering iron

When soldering chip devices, use the correct soldering iron.

- Soldering iron
  The power of the soldering iron should be less than 30 watts. The diameter of the iron should be about 2 mm.
- Temperature of iron tip.
  The temperature of the soldering iron tip should be less than 536°F. (280°C)

e. Mounting chip device onto printed circuit board

- Set chip devices as close as possible to the surface of the printed circuit board.
  Do not apply unnecessary pressure to chip devices to try to make it close to the surface of printed circuit board.
  Try to keep the distance between the chip device and the surface of the printed circuit board less than 0.5mm.
- Do not connect (solder) wire or terminals of otherparts to a terminal of a chip device.
- Do not mount chip devices incorrectly, such as in (b), (c) and (d), below.



Fig. 6

f. Removal of defective device for repair

When removing chip devices with a fork tipped iron, heat the chip device with the fork tip and slide the chip device off.
When you are going to remove the chip devices using a regular tipped iron, alternately heat the two terminals of the chip device about 2 or 3 times and slide the chip device off. Slide chip device only in the direction shown below.



Fig. 7

■ ADJUSTMENTS

Voltage adjustment

- Use to make connection between the Main Circuit Board and the DSP Circuit Board.
  5P Extention cord (P/No. VB711700)
  8P Extention cord (P/No. VB717100)
- Set DC power supply voltage to 14.4V, with no load or signal applied.
- Measure the voltage at the test point +5D and adjust the VR601 so that the following rating will be satisfied.

$$V_{5D} = 5 \pm \frac{0.2}{0.1} \text{ V (DC)}$$



e. Mounting chip device onto printed circuit board

- Set chip devices as close as possible to the surface of the printed circuit board.
  Do not apply unnecessary pressure to chip devices to try to make it close to the surface of printed circuit board.
  Try to keep the distance between the chip device and the surface of the printed circuit board less than 0.5mm.
- Do not connect (solder) wire or terminals of otherparts to a terminal of a chip device.
- Do not mount chip devices incorrectly, such as in (b), (c) and (d), below.



Fig. 6

f. Removal of defective device for repair

When removing chip devices with a fork tipped iron, heat the chip device with the fork tip and slide the chip device off.
When you are going to remove the chip devices using a regular tipped iron, alternately heat the two terminals of the chip device about 2 or 3 times and slide the chip device off. Slide chip device only in the direction shown below.



Fig. 7

■ ADJUSTMENTS

Voltage adjustment

- Use to make connection between the Main Circuit Board and the DSP Circuit Board.
  5P Extention cord (P/No. VB711700)
  8P Extention cord (P/No. VB717100)
- Set DC power supply voltage to 14.4V, with no load or signal applied.
- Measure the voltage at the test point +5D and adjust the VR601 so that the following rating will be satisfied.

$$V_{SD} = 5 \pm \frac{0.2}{0.1}\ V\ (DC)$$



Main Circuit Board (Part side)

1. S-RAM Check

When turning ON the power of this unit for the first time, S-RAM check should be done at the same time according to the procedure described below.

① Turn ON the power.
Confirm that "HELP!" appears on display.
② Turn OFF the power.
③ Turn ON the power.
Confirm that the mode is set to HALL.

If "HELP!" appears in above Step ③, an abnormality exists in either the S-RAM itself or its peripheral.

When the S-RAM check results (Steps ① to ③) are satisfactory, proceed to the test program described.

④ Proceeding to the test program while "HELP!" is on display will result in the "ERROR" display. When the key operation is not accepted, the communication condition between the main unit and the commander is poor.

2. Test Program

1. Starting

Turn ON the power, press the "memo" key and within 5 seconds, press the "AUDIO" key. Then pressing the "reset" key within 10 seconds will start the program.

2. Error check

The test program executes the error check and displays the error, if any, by using the following error messages.

Error message	Check Content
ERROR 1	ROM error
ERROR 2	CPU internal RAM error
ERROR 3	External RAM error
ERROR 4	Back-up error
ERROR 5	DEQ, DSP transfer error

3. Test Mode Menu

The test mode has following menu items.
(1) LCD check
(2-1) RAM through
(2-2) DSP through
(3) EQ check
(4) VOL UP/DOWN
(5) MUTE ON/OFF

The initial conditions are as follows.

- **LCD display : RAM**
- **LED : Green**
- **Signal : RAM through**
- **EQ : Flat**
- **VOL : Max.**
- **MUTE : OFF**
- **BAL/FAD : Center position**

(1) LCD check

With the test program started, pressing the "POSITION" key will cause all LCDs to light.

(2) Signal check

0dB should be obtained at every channel under the following conditions.
EQ : Flat
BAL/FAD : Center position
VOL : 0

1) RAM through

When the test program is started, "RAM" appears on display and the signal is obtained in the RAM through state. After that, the signal state is switched between DSP through and RAM through at every pressing of the "DSP ON" key. In the RAM through state, about 186ms delay occurs.



2) DSP through

When the "DSP ON" key is pressed in the RAM through state, "DSP" appears on display and the signal state becomes the DSP through state.
After that, the signal state is switched between DSP through and RAM through at every pressing of the "DSP ON" key.



(3) EQ check

Pressing the "EQ (ON/OFF)" key sets to DSP through state and 1kHz EQ measurement mode. When the parameter "+" key is pressed, the frequency gain which is flashing then increases by 12dB and when the "–" key is pressed it decreases by 12dB, resulting in 0dB. Pressing the "–" key again will result in -12dB. When the "P.SEL" key is pressed, the frequency shifts to the right by one and at the same time all bands become flat.

(4) VOL UP/DOWN

The volume is at maximum(0) when the test program is started. It varies as the " △ " " ▽ " key is used.

(5) MUTE ON/OFF

Pressing the "MUTE" key will result in 20dB decrease . The MUTE display flashes during MUTE ON.

4. Terminating Test Program

Be sure to press the "RESET" key at the end of the test program.

■ PRINTED CIRCUIT BOARD (Foil side)

I/O C. B



Commander C. B

① to ④ : WAVEFORM OF TEST POINT (See page 24)



■ PRINTED CIRCUIT BOARD (Foil side)

⑤ to ⑪ : WAVEFORM OF TEST POINT (S



● **Semiconductor Location**

Ref. No.	Location	Ref. No.	Location	Ref. No.	Location	Ref. No.	Location
D 347	D2	D 610	B3	IC 312	D4	IC 609	A2
D 601	B3	D 650	B4	IC 313	B4	IC 610	B2
D 603	A4	D 651	B4	IC 315	B4	IC 611	B3
D 604	B4	D 653	B5	IC 316	C4	Q 601	B4
D 607	A3	IC 308	C3	IC 326	B2	Q 607	A4
D 609	A3	IC 309	C3	IC 604	A4	Q 608	A4

e page 22 and 23)



● **Semiconductor Location**

Ref. No.	Location
IC 1	F2
IC 3	F2
IC 4	G2
IC 5	G2
IC 6	G3
IC 7	G3

Ref. No.	Location
IC 9	F3
IC 10	F4
IC 11	E3
IC 12	F3
IC 13	F4
IC 14	F3

Ref. No.	Location
IC 15	F3
IC 24	G4
IC 28	F2
IC 29	E2
IC 31	F2
IC 32	E2

Ref. No.	Location
IC 34	F3
IC 38	F3
IC 41	F3

- **SW1**

  This unit has a SW1 for the servicing purpose.
  Sliding it to the opposite side of the IC11 allows the output to come through the DSP and DEQ circuits. This facilitates determination whether a failure exists in the DSP and DEQ circuits (including ICs) or elsewhere. Be sure to slide it back to the IC11 side after completion of the repair work.

■ PRINTED CIRCUIT BOARD (Foil side)

MAIN C. B



● Semiconductor Location

Ref. No.	Location
D 312	B4
D 346	B4
D 481	D2
D 508	B4
D 602	A4
D 605	B2
D 649	B4

Ref. No.	Location
IC 301	B2
IC 302	C2
IC 303	C3
IC 305	C2
IC 307	C3
IC 317	D4
IC 322	D4

Ref. No.	Location
IC 324	D2
IC 327	D4
Q 303	B3
Q 304	C2
Q 305	B3
Q 306	B3
Q 481	D2

Ref. No.	Location
Q 602	B4
Q 603	B2
Q 612	B2
Q 614	B2
Q 615	B2

DSP C. B



● **Semiconductor Location**

Ref. No.	Location
IC 17	G4
IC 19	F4
IC 23	G3
IC 33	F2
IC 37	F2
IC 42	F2

■ INTERCONNECT WIRING DIAGRAM



■ IC DATA

IC312 (MAIN) : Useable for all HD63B01Y0XXXXP series.
8 bit μ-COM





Pin No.	Pin Name	Description	I/O	Function
1	VSS	VSS	—	Ground
2	XTAL	XTAL	—	Oscillation circuit
3	EXTAL	EXTAL	—	Oscillation circuit
4	MP0	MP0	—	Mode program input. Fixed to "H"
5	MP1	MP1	—	Mode program input. Fixed to "L"
6	$\overline{RES}$	IC#	—	Reset input (Negative logic)
7	$\overline{STBY}$	STBY#	—	Stand-by input (Negative logic)
8	$\overline{NMI}$	RESET	—	$\overline{NMI}$ input (Negative logic) Used for resetting equipment.
9	P20	CEC	O	LCD driver (C) chip enable

Pin No.	Pin Name	Description	I/O	Function
10	P21	COO	I	Bit O input of DEQ coefficient RAM
11	P22	LCLK	O	Clock for LCD driver
12	P23		I	Communication input
13	P24	DATA	O	Communication output
14	P25	CEA	O	DA control output
15	P26	CEB	O	DA control output
16	P27	DI0	—	Unused
17	P50	DI1	—	
18	P51	DI2	—	
19	P52	DI3	I	Overflow input pull-down
20	P53	DI4	I	Halt input
21	P54	K0	—	Unused
22	P55	K1	—	
23	P56	K2	—	
24	P57	K3	—	
25	P60	CONTROL	I	DA control input
26	P61	EMP	—	Unused
27	P62	ERR	—	
28	P63	FS0	—	
29	P64	FS1	—	
30	P65	DI	O	Data for volume IC
31	P66	VCLK	O	Clock for volume IC
32	P67	CE	O	Chip enable for volume IC
33	VCC	VCC	—	Power source
34	A15	A15	—	Address bus
35	A14	A14	—	
36	A13	A13	—	
37	A12	A12	—	
38	A11	A11	—	
39	A10	A10	—	
40	A9	A9	—	
41	A8	A8	—	
42	VSS	VSS	—	Ground
43	A7	A7	—	Address bus
44	A6	A6	—	
45	A5	A5	—	
46	A4	A4	—	
47	A3	A3	—	
48	A2	A2	—	
49	A1	A1	—	
50	A0	A0	—	
51	D7	D7	—	Data bus
52	D6	D6	—	
53	D5	D5	—	
54	D4	D4	—	
55	D3	D3	—	
56	D2	D2	—	
57	D1	D1	—	
58	D0	D0	—	
59	BA		—	Unused
60	$\overline{LIR}$		—	
61	R/$\overline{W}$		—	
62	$\overline{WR}$	$\overline{WR}$	—	
63	$\overline{RD}$	$\overline{RD}$	—	
64	E	E	—	

IC1 (COMMANDER) : HD63B01YORAA6FJ
8bit μ-COM





Pin No.	Pin Name	Description	I/O	Function
1	Vss	Vss	—	Ground
2	XTAL	XTAL	—	Oscillation circuit
3	EXTAL	EXTAL	—	Oscillation circuit
4	MP0	MP0	—	Mode program input. Fixed to "H"
5	MP1	MP1	—	Mode program input. Fixed to "L"
6	$\overline{RES}$	IC#	—	Reset input (Negative logic)
7	$\overline{STBY}$	STBY#	—	Stand-by input (Negative logic)
8	$\overline{NMI}$	RESET	—	$\overline{NMI}$ input (Negative logic) Used for resetting equipment.
9	P20	CEC	O	LCD driver (C) chip enable

Pin No.	Pin Name		I/O	ACT	Function
10	P50	K0	I	H	Key scan input
11	P51	K1			
12	P52	K2			
13	P53	K3			
14	P54				Pull-up to high level
15	P55				
16	P56				
17	P57				
18	P60	DI0	O	H	Key scan output
19	P61	DI1			
20	P62	DI2			
21	P63	DI3			
22	P64	DI4			
23	P65				NC
24	P66				
25	P67				
26	VCC	VCC			Power terminal (+5V)
27	P47				NC
28	P46				
29	P45				
30	P44				
31	P43				
32	P42	$\overline{INH}$	O	L	LCD driver $\overline{INH}$ output
33	P41				NC
34	P40				
35	VSS	VSS			GND terminal
36	P17				NC
37	P16				
38	P15				
39	P14				
40	P13				
41	P12				
42	P11				
43	P10				
44	P37				
45	P36				
46	P35				
47	P34				
48	P33				
49	P32				
50	P31				
51	P30				
52	P74				
53	P73				
54	P72				
55	P71				
56	P70				
57	E				
58	VSS	VSS			GND terminal
59	XTAL	XTAL			Crystal connection terminal
60	EXTAL	EXTAL			
61	MP0	MP0			Mode setting terminal
62	MP1	MP1			Single chip mode at (1,1)
63	$\overline{RES}$	$\overline{RES}$	I	L	Reset input terminal
64	$\overline{STBY}$	$\overline{STBY}$	I	L	Stand-by input terminal (fixed to high level)

IC6, 7 : YM6104
Digital Equalizer





Pin No.	Pin Name	I/O	Function
1	VDD	I	+5V power supply
2	XMD	I	Switches CDI input to either synchronous mode (1 : 1) "L" or asynchronous mode (Start-stop synchronous system 16 : 1) "H"
3	$\overline{CRS}$	I	Initializes SCI interface
4	CDI	I	SCI input for setting micro program, factor and control register
5	CDO	O	SCI output for setting micro program, factor and control register
6	XCLK	I	Input-output clock for CDI and CDO
7	TRG	I	Determines parameter transfer timing from transfer buffer to factor RAM when external trigger is selected
8	ESL	I	Enters output timing into SO0 and SO1 when EXT clock is selected
9	ELD	I	Enters input timing into SI0 and SI1 when EXT clock is selected
10	ECLK	I	Enters input-output clock for SI0, SO0 and SO1 when EXT clock is selected
11	CLK	I	Master clock input
12	VSS	I	Ground
13, 14	SI0, SI1	I	16 bits serial input
15, 16	SO0, SO1	O	16 bits serial output
17	$\overline{OVF}$	O	Over flow detect
18	$\overline{TEST}$	I	Used for testing Usually connected to +5V
19	C2/Sign	O	Outputs bit 2 of factor RAM while delaying it by 1 bit. Used as a timing signal Monitors sign bit of accumulator by setting test Reg (When factor RAM is used as a timing signal, effective bit number of factor decreases)
20	C1/TESTM	O	Outputs bit 1 of factor RAM while delaying it by 1 bit. Used as a timing signal Switches to test output of multiplier by setting test Reg
21	CO	O	Outputs bit 2 of factor RAM while delaying it by 1 bit. Can be used as a timing signal
22	CEMD	I	Turns OFF CE of SCI input CE ON : "H" CE OFF : "L"
23	$\overline{IC}$	I	Initializes DEQ operation
24	$\overline{Sync}$	I	Synchronous signal of system

IC9, 12 : YM3413
LDSP



Pin No.	Pin Name	I/O	Function	Pin No.	Pin Name	I/O	Function
1	VDD	—	+5V voltage supply	40	CLK	I	Master clock input
2	D7	I/O	I/O pins connected to memory data bus (8bit)	39	SO1	O	Serial data output
3	D6	I/O		38	CDO	O	CD data output
4	D5	I/O		37	CDI	I	CD data input
5	D4	I/O		36	CRS	I	CD data sync signal input
6	D3	I/O		35	IC	I	LDSP initial clear signal input
7	D2	I/O		34	XCLK	I	ACIA clock input
8	D1	I/O		33	SDO	O	Serial data output
9	D0	I/O		32	A16	O	Outputs connected to memory address bus
10	SI0	I	Serial data input	31	A15	O	
11	SI1	I		30	A14	O	
12	SYW	I	System sync signal input	29	A13	O	
13	WE	O	Read/write signal to memory input	28	A12	O	
14	OE	O	Pin connected to memory OE term	27	A11	O	
15	A0	O	Outputs connected to memorys address bus	26	A10	O	
16	A1	O		25	A9	O	
17	A2	O		24	A8	O	
18	A3	O		23	A7	O	
19	A4	O		22	A6	O	
20	VSS	O	GND 0V	21	A5	O	

IC11 : YM3422
Digital Signal Format Converter





Pin No.	Pin Name	I/O	Function
1	VSS	—	GND terminal
2	SI0	IN	Serial data input (ch 0)
3	SO0	OUT	Serial data output (ch 0)
4	BC0	IN	Bit clock input
5	WC0	IN	System synchronized signal input
6	SI2	IN	Serial data input (ch 0)
7	SO2	OUT	Serial data output (ch 0)
8	VDD	—	Voltage supply (+5V)
9	MO	IN	Mode select signal
10	M1	IN	
11	M2	IN	
12	M3	IN	
13	WC1	IN	System synchronized signal input (Word clock)
14	BC1	IN	Bit clock input
15	SC1	IN	Serial data output (ch 1)
16	SI1	OUT	Serial data input (ch 1)

IC24 : YM3436
Digital Format Interface Receiver





Pin No.	Pin Name	I/O	Function	Pin No.	Pin Name	I/O	Function
1	NC			33	NC		
2	NC			34	NC		
3	NC			35	NC		
4	DB11	O	Meter data output	36	DI00	I	Digital in data
5	DB10	O		37	DI01	I	
6	DB9	O		38	DI02	I	
7	DB8	O		39	DI03	I	
8	DB7	O		40	DI04	I	
9	DB6	O		41	DI05	I	
10	NC			42	NC		
11	DB5	O		43	DI06	I	
12	DB4	O		44	DI07	I	
13	DB3	O		45	DI08	I	
14	DB2	O		46	DI09	I	
15	DB1	O		47	DI10	I	
16	DB0	O		48	DI11	I	
17	NC			49	NC		
18	NC			50	NC		
19	NC			51	NC		
20	NC			52	NC		
21	$\overline{OVD}$	I	Overflow data	53	HT1	I	Falling and holding times are determined by these inputs.
22	OMODE	I	Output mode control	54	HT0	I	
23	IMODE	I	Input mode control	55	FT1	I	
24	NC			56	FT0	I	
25	$\overline{TST}$	I	Test pin	57	VSS		Ground
26	VDD		Power supply	58	VDD		Power supply
27	VSS		Ground	59	NC		
28	ICLK	I	System clock input	60	C3	O	Channel select
29	$\overline{SYNC}$	I	Synch. pulse	61	C2	O	
30	$\overline{RST}$	I	Initial reset	62	C1	O	
31	$\overline{DIEN}$	I	Digital input enable	63	C0	O	
32	NC			64	NC		